arXiv:1203.4044v1 [math.NA] 19 Mar 2012

Domain Decomposition Preconditioners for a Discontinuous Galerkin Formulation of a Multiscale Elliptic Problem

Yunfei Ma, Petter Bjørstad, Talal Rahman, and Xuejun Xu

Abstract

In this paper, we propose a domain decomposition method for multiscale second order elliptic partial differential equations with highly varying coefficients. The method is based on a discontinuous Galerkin formulation. We present both a nonoverlapping and an overlapping version of the method. We prove that the condition number bound of the preconditioned algebraic system in either case can be made independent of the coefficients under certain assumptions. Also, in our analysis, we do not need to assume that the coefficients are continuous across the coarse grid boundaries. The analysis and the condition number bounds are new, and contribute towards further extension of the theory for the discontinuous Galerkin discretization for multiscale problems.

1 Introduction

Subsurface flows in heterogenous media [9, 10], that is, where the heterogeneity varies over a wide range of scales, are examples of multiscale problems. Numerical solutions of such problems are often affected by the heterogeneity, in particular when it is highly varying, that is, the permeability of the media can span a large scale. In this paper we consider the numerical solution of flow problems governed by elliptic equations with highly varying coefficients. Domain decomposition methods use both fine scale and coarse scale subproblems as well as interpolation operators from the subspaces to the solution space to construct preconditioners for the original problem. The convergence property is linked to proper treatment of the jumps in the coefficients [5]. A key point when building such domain decomposition methods is to find a good coarse problem that can capture relevant small scale information from the fine level. In general, due to the complex geometry of the conductivity field, where high and low conductivity regions often appear as small inclusions inside subdomains and long channels across subdomain boundaries, it is rather difficult to design a robust domain decomposition method for such problems.

When considering high conductivity regions (inclusions or channels) in a low conductivity background, the authors of [5] used functions that are discrete harmonic in each coarse grid block with special boundary values as coarse basis functions (multiscale basis functions). They introduced two indicators, $\pi(\alpha)$ and $\gamma(\alpha)$, where α is the coefficient representing the conductivity, to capture the effect of the jumps in α on the condition number. The indicator $\pi(\alpha)$ measures how well the coarse partitioning of the whole domain Ω is, as for instance, $\pi(\alpha)$ behaves well as long as the high conductivity regions (inclusions) do not cross any subdomain boundaries, and badly otherwise. The indicator $\gamma(\alpha)$ is a measure for the weighted energy norm of the coarse basis functions, and it depends on the choice of boundary conditions, as for instance, an oscillatory boundary condition is often needed in order to keep the energy norm low, consequently for $\gamma(\alpha)$ to behave well. The authors in [5] used the traditional L^2 projection operator from the fine space to the coarse space, and proved that the condition number bound is independent of the jumps. This approach assumes that the conductivity coefficient is continuous across coarse grid boundaries, although their numerical results did not seem to require this. Recently, in [11], the authors proposed an overlapping domain decomposition method for the multiscale problem. The idea of their method is based on the fact that high conductivity regions correspond to the smallest eigenvalues of the system. Consequently, they used the corresponding eigenfunctions as coarse basis functions, and proved a weighted Poincaré inequality resulting in a condition number bound independent of the jumps. They also proposed an overlapping domain decomposition methods for the Schur complement system.

Discontinuous Galerkin methods may offer several important and valuable computational advantages over their conforming Galerkin counterparts. The finite element spaces are not subject to inter-element continuity conditions, and the local element spaces can be defined independently. This makes discontinuous Galerkin methods well suited for their applications to multiscale problems with piecewise constant coefficients relative to a fine triangulation. A domain decomposition method for the discontinuous Galerkin formulation of a multiscale elliptic problem has recently been proposed in [4]. There a composite discontinuous Galerkin formulation, that is, a regular continuous formulation inside each subdomain and a discontinuous Galerkin formulation across the subdomain boundaries, has been used. There the coarse space consists of piecewise constant basis functions over the coarse partition. The condition number bound of this method is shown to be

$$\max_i \max_j \frac{\overline{\alpha}_i}{\underline{\alpha}_i} \frac{H_i}{h_i h_{ij}}, \tag{1.1}$$

where $\overline{\alpha}_i$ and $\underline{\alpha}_i$ represent the maximum and the minimum of the coefficients inside a boundary layer of the subdomain Ω_i, H_i is the diameter of Ω_i, h_i is the fine mesh size in Ω_i, and $h_{ij} = 2h_i h_j/(h_i+h_j)$, the harmonic average of h_i and h_j. We note that the condition number bound above depends on the jump of the coefficients inside the boundary layer of each subdomain.

The present work is an extension of the work in [5] to a discontinuous Galerkin formulation. We use the same bilinear form as the one given in [13] with harmonic average weight functions, defined on the fine space which is the space of piecewise linear polynomials with respect to the fine triangulation. A composite discontinuous Galerkin formulation, c.f., [4], is used on the coarse space whose basis functions are the multiscale basis functions given by the oscillatory boundary conditions, c.f., [5]. We present both a nonoverlapping and an overlapping method.

A new indicator $\beta(\alpha)$ is introduced measuring the L^2 norm of the jump of the coarse basis functions across coarse grid boundaries (see (3.11)). We show that, under certain assumptions, slightly weaker than in [5], our methods are robust. For the nonoverlapping case, we show that the condition number bound is

$$\eta \max_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} W_e \gamma(1) \frac{H}{h} + \max\big(\gamma(\alpha), \eta\beta(\alpha)\big), \tag{1.2}$$

where W_e is the harmonic average weight function (see (2.3)), $\gamma(\alpha)$ and $\beta(\alpha)$ are the indicators, and η is a penalty parameter. The numerical experiments support the assumption that this bound is sharp. However, due to the presence of W_e in the bound, the method may have a large condition number when high conductivity channels cross subdomain boundaries. Note that, this is the case for (1.1) even when there are no channels crossing subdomain boundaries. The situation gets improved in the overlapping case. We show that, for the overlapping method, the condition number bound is

$$\pi(\alpha)\max\big(\gamma(1),\beta(1)\big)\max_i\frac{H_i}{\delta_i}+\max\big(\gamma(\alpha),\eta\beta(\alpha)\big). \tag{1.3}$$

The rest of the paper is organized as the following. In Section 2, we introduce our model problem and the discontinuous Galerkin discrete formulation. The two level additive Schwarz domain decomposition methods, first the nonoverlapping and then the overlapping version, are defined and analyzed in Section 3. Section 4 is devoted to the numerical results.

2 Problem Setting

Throughout this paper, we adopt standard notations from the Lebesgue and Sobolev space theory (see [1]). We further use $A \lesssim B$ to denote $A \leq CB$ with a positive constant C depending only on the shape regularity of the meshes, and $A \approx B$ to denote $A \lesssim B \lesssim A$.

Consider the self adjoint elliptic problem on a polygonal domain Ω with boundary $\partial\Omega$,

$$L(u) = -\nabla\cdot(\alpha(x)\nabla u) = f, \quad x \in \Omega, \tag{2.1}$$

$$u = g, \quad x \in \partial\Omega, \tag{2.2}$$

where the coefficient $\alpha(x) \in L^\infty(\Omega)$ with $\alpha(x) \geq \alpha_0 > 0$, representing the conductivity field on Ω, is piecewise constant on the fine mesh $\mathcal{T}_h$, $\alpha(x)$ may have (discontinuous) jumps across the elements. Also we let $f \in L^2(\Omega)$.

First, we introduce some notations. $\mathcal{T}_h$ denotes a fine triangulation of the whole domain Ω which is quasi-uniform, $\mathcal{T}_h = \bigcup_{\tau\in\Omega}\tau$, where τ represents a small triangle in $\mathcal{T}_h$ and h is the mesh size. $\mathcal{T}_H$ denotes a coarse triangulation which we get by partitioning Ω into triangular substructures $\mathcal{T}_H$, which is also quasi-uniform with the mesh size H. We assume that the boundary edge of each coarse grid element in $\mathcal{T}_H$, is aligned with the edges of the elements in the fine triangulation $\mathcal{T}_h$. We denote the elements of the coarse and the fine triangulation by K, and τ, respectively. e denotes an edge of a fine element τ, and $\mathcal{E}$ is the union of all edges in Ω, $\mathcal{E} = \bigcup_{e\subset\partial\tau} e$. Additionally, $\mathcal{E} = \mathcal{E}_I \bigcup \mathcal{E}_D$, where $\mathcal{E}_I := \bigcup_{j>l} e_{jl}$ refers to all the inner edges and $\mathcal{E}_D := \bigcup_{e\subset\partial\Omega} e$ refers to all the edges touching $\partial\Omega$. Given a coarse triangulation $\mathcal{T}_H = \{K_i\}_{i=1}^N$, we let ∂K_i be the boundary of the element K_i, and $\partial K_{ij} = \partial K_i \cap \partial K_j$ be the open edge shared by the elements K_i and K_j.

Next, we introduce two weight functions related to each fine edge $e \in \mathcal{E}_I$. We first denote the two fine elements sharing an edge e by τ_+^e and τ_-^e, and denote the coefficients of the two elements by α_+^e and α_-^e respectively. The weight functions w_+^e and w_-^e, associated with the edge e, are defined as

$$w_+^e + w_-^e = 1,$$

where $w_+^e = \alpha_-^e/(\alpha_+^e + \alpha_-^e)$ and $w_-^e = \alpha_+^e/(\alpha_+^e + \alpha_-^e)$. The harmonic average weight function, associated with the edge e, is then

$$W_e = w_+^e\alpha_+^e + w_-^e\alpha_-^e = \frac{2\alpha_-^e\alpha_+^e}{\alpha_-^e + \alpha_+^e}. \tag{2.3}$$

The following inequalities hold,

$$\frac{(w_+^e)^2\alpha_+^e}{W_e} = \frac{(w_+^e)^2\alpha_+^e}{w_+^e\alpha_+^e + w_-^e\alpha_-^e} \leq \frac{(w_+^e)^2\alpha_+^e}{w_+^e\alpha_+^e} \leq w_+^e \leq 1, \tag{2.4}$$

and

$$\frac{(w_-^e)^2\alpha_-^e}{W_e} \leq 1.$$

Now, let $\alpha_{min} = \min(\alpha_-^e, \alpha_+^e)$ and $\alpha_{max} = \max(\alpha_-^e, \alpha_+^e)$, it then follows immediately that $\alpha_{min} \leq W_e \leq 2\alpha_{min}$. In the above definitions of W_e and w^e, for $e \in \mathcal{E}_D$, we set $w_e = 1$ and $W_e = \alpha^e$.

Let the jump across an edge e be

$$[v] = \begin{cases} v_+^e \mathbf{n}_+^e + v_-^e \mathbf{n}_-^e, & e \in \mathcal{E}_I, \\ v_e \mathbf{n}_e, & e \in \mathcal{E}_D, \end{cases} \tag{2.5}$$

where $\mathbf{n}_+^e$ and $\mathbf{n}_-^e$ denote the unit outward normal vectors of τ_+^e and τ_-^e, respectively. The weighted average $\{v\}_w^e$ is defined similarly by

$$\{v\}_w^e = \begin{cases} w_+^e v_+^e + w_-^e v_-^e, & e \in \mathcal{E}_I, \\ w_e v_e, & e \in \mathcal{E}_D. \end{cases} \tag{2.6}$$

For the ease of our presentation, we define all our norms and function spaces here.

Given a domain $D \subset \Omega$, we define the standard L^∞ norm on D as

$$||u||_{0,\infty,D}^2 := \text{ess sup}\{|u(x)| : x \in D\},$$

and the standard L^2 norm on D as

$$||u||_{0,D}^2 := \int_D u^2 dx.$$

A weighted H^1 seminorm on D is defined by

$$|u|_{1,\alpha,D}^2 := \int_D \alpha \nabla u \cdot \nabla u \, dx,$$

where $\alpha(x) > 0, \ \forall x \in D$. With $\alpha(x) = 1, \ \forall x \in D$, we get the standard H^1 seminorm

$$|u|_{1,D}^2 := \int_D \nabla u \cdot \nabla u \, dx.$$

A weighted norm, based on the discontinuous Galerkin formulation, on D, is defined by

$$\|u\|_{1,h,\alpha,D}^2 := \sum_{\tau \subset D} \int_\tau \alpha \nabla u \cdot \nabla u dx + \sum_{\substack{e_{jl} \subset D \\ j > l}} \frac{W_e}{h_e} \|[u]\|_{0,e}^2 + \sum_{e \subset \partial D} \frac{W_e}{h_e} \|u_e\|_{0,e}^2,$$

where $\bigcup_{j>l} e_{jl}$ refers to all the fine element edges in the interior of D. We use

$$|u|_{1,h,\alpha,D}^2 := \sum_{\tau \subset D} \int_\tau \alpha \nabla u \cdot \nabla u dx + \sum_{\substack{e_{jl} \subset D \\ j > l}} \frac{W_e}{h_e} \|[u]\|_{0,e}^2$$

to denote the corresponding semi norm on D. If $\alpha(x) = 1,\ \forall x \in D$, we get the following norm

$$\|u\|_{1,h,D}^2 := \sum_{\tau \subset D} \int_\tau \nabla u \cdot \nabla u dx + \sum_{\substack{e_{jl} \subset D \\ j>l}} \frac{1}{h_e} \|[u]\|_{0,e}^2 + \sum_{e \subset \partial D} \frac{1}{h_e} \|u_e\|_{0,e}^2,$$

and seminorm

$$|u|_{1,h,D}^2 := \sum_{\tau \subset D} \int_\tau \nabla u \cdot \nabla u dx + \sum_{\substack{e_{jl} \subset D \\ j>l}} \frac{1}{h_e} \|[u]\|_{0,e}^2.$$

Let $H^s(\mathcal{T}_h)$ be a broken Sobolev space of degree $s > 0$ defined as

$$H^s(\mathcal{T}_h) = \{v \in L^2(\Omega) : v|_\tau \in H^s(\tau),\ \forall \tau \in \mathcal{T}_h\},$$

and $V^s(\mathcal{T}_h)$ be its subspace defined as

$$V^s(\mathcal{T}_h) = \{v \in H^s(\mathcal{T}_h) : \nabla \cdot (\nabla v) \in L^2(\tau),\ \forall \tau \in \mathcal{T}_h\}.$$

With the above preparation, we can now define our discontinuous Galerkin bilinear form $a(u, v)$ and the right hand side $f(v)$ for the continuous problem (2.1) and (2.2). They are defined as follows, c.f., [13]. For $u, v \in V^{1+\epsilon}(\mathcal{T}_h)$,

$$\begin{aligned} a(u,v) =& \sum_\tau \int_\tau \alpha \nabla u \cdot \nabla v dx - \sum_{\substack{e_{jl} \subset \Omega \\ j>l}} \int_{e_{jl}} \{\alpha \nabla u\}_w^e [v] ds - \sum_{\substack{e_{jl} \subset \Omega \\ j>l}} \int_{e_{jl}} \{\alpha \nabla v\}_w^e [u] ds \\ &+ \eta \sum_{\substack{e_{jl} \subset \Omega \\ j>l}} \frac{W_e}{h_e} \int_{e_{jl}} [u][v] ds - \sum_{e \subset \partial\Omega} \int_e w_e \alpha_e \nabla u_e \cdot v_e \mathbf{n}_e ds \\ &- \sum_{e \subset \partial\Omega} \int_e w_e \alpha_e \nabla v_e \cdot u_e \mathbf{n}_e ds + \eta \sum_{e \subset \partial\Omega} \frac{W_e}{h_e} \int_e u_e v_e ds, \end{aligned} \tag{2.7}$$

and

$$f(v) = \sum_\tau \int_\tau f v dx - \sum_{e \subset \partial\Omega} \frac{W_e}{h_e} \int_e g(\alpha \nabla v \cdot \mathbf{n}_e) ds + \eta \sum_{e \subset \partial\Omega} \frac{W_e}{h_e} \int_e g v ds,$$

where $\cup_{j>l} e_{jl}$ refers to all the fine element edges in the interior of Ω, W_e is the harmonic weight function defined in (2.3), and η is a penalty parameter.

Here and in the text below, for simplicity, we use W_e, h_e and $\{\cdot\}_w^e$ instead of $W_{e_{jl}}$, $h_{e_{jl}}$ and $\{\cdot\}_w^{e_{jl}}$ respectively if there is no confusion. Moreover, as stated in [13], for $f \in L^2(\Omega)$, the flux $\sigma = -\alpha \nabla u$ is in $H(\text{div}; \Omega) \cap H^\epsilon(\mathcal{T}_h)^2$, where $H(\text{div}; \Omega) = \{\mathbf{v} \in L^2(\Omega)^2 : \nabla \cdot \mathbf{v} \in L^2(\Omega)\}$ is an Hilbert space equipped with the norm $||\mathbf{v}||_{H_{\text{div};\Omega}} = (||\mathbf{v}||_{0,\Omega}^2 + ||\nabla \cdot \mathbf{v}||_{0,\Omega}^2)^{1/2}$. The integrations on the fine edge e_{jl} in (2.7) above can be understood in the weak sense, see [13] for details.

Due to [13], the the weak solution of (2.1) and (2.2), $u \in H^{1+s}(\Omega) \cap V^{1+\epsilon}(\mathcal{T}_h)$, $0 < \epsilon \leq s \leq 1$, satisfies the following variational equation

$$a(u, v) = f(v),\ \forall v \in V^{1+\epsilon}(\mathcal{T}_h). \tag{2.8}$$

Next, we define the finite element space V^h associated with $\mathcal{T}_h$ as follows. For any fine triangle τ let $P_1(\tau)$ denote the set of all linear polynomials on τ. The finite element space V^h is then defined as

$$V^h = \{v : v|_\tau \in P_1(\tau),\ \forall \tau \in \mathcal{T}_h\}.$$

The bilinear form on the finite element space V^h is defined as $a_h(u,v) = a(u,v)$, $\forall u, v \in V^h$.

We can now formulate our discrete problem: Find $u_h \in V^h$ such that

$$a_h(u_h, v_h) = f(v_h),\ \forall v_h \in V^h. \tag{2.9}$$

Naturally, the above bilinear form induces a norm in the space V_h, which is

$$\|v\|^2_{1,h,\alpha,\Omega} = \sum_{\tau\subset\Omega} \int_\tau \alpha \nabla v \cdot \nabla v dx + \sum_{\substack{e_{jl}\in\subset\Omega \\ j>l}} \frac{W_e}{h_e} \|[v]\|^2_{0,e} + \sum_{e\subset\partial\Omega} \frac{W_e}{h_e} \|v_e\|^2_{0,e}.$$

The next lemma gives us the continuity and coercivity of the bilinear form $a_h(\cdot,\cdot)$.

Lemma 2.1. *There exists a constant C, such that*
(i)
$$|a_h(u,v)| \le C||u||^2_{1,h,\alpha,\Omega}||v||^2_{1,h,\alpha,\Omega},\ \forall u, v \in V^h.$$

(ii) *There exists positive constant $\eta_0 > 0$, such that for all $\eta > \eta_0$,*

$$a_h(u,u) \ge C(\eta)||u||^2_{1,h,\alpha,\Omega},\ \forall u \in V^h,$$

where $C(\eta)$ is independent of the jump in the coefficient.

As a consequence of the above lemma, (2.9) has a unique solution. The proof of Lemma 2.1 as well as an error estimate is given in [13].

3 The Schwarz methods

In this section, we use the Schwarz framework [2, 12] to design and analyze our additive Schwarz domain decomposition methods for the discontinuous Galerkin formulation. Let Ω be partitioned into a family of nonoverlapping open subdomains $\{\Omega_i, 1 \le i \le N\}$ with

$$\overline{\Omega} = \bigcup_{i=1}^{N} \overline{\Omega_i},\ \Omega_i \cap \Omega_j = \emptyset,\ i \ne j.$$

Next, we give the overlapping partition $\{\Omega'_i\}_{i=1}^N$ by extending each subregion Ω_i into a larger region Ω'_i, i.e., $\Omega_i \subset \Omega'_i$, so that

$$\overline{\Omega} = \bigcup_{i=1}^{N} \Omega'_i.$$

We assume that both the nonoverlapping and overlapping partition are aligned with $\mathcal{T}_h$ and $\mathcal{T}_H$. We denote by δ the minimum of the distance between the boundaries of Ω_i and Ω'_i, i.e., $\delta = \min\ \mathrm{dist}(\partial\Omega'_i\backslash\partial\Omega, \partial\Omega_i\backslash\partial\Omega)$. If there exists a constant number $C > 0$ such that $\delta \ge CH$, we say that $\{\Omega'_i\}_{i=1}^N$ has generous overlap, and if δ is proportional to h, we say it has small overlap.

Following the Schwarz framework, the space V^h is split into a number of local subspaces and a global coarse space, i.e., $V^h = V_0 + \sum_{i=1}^N V_i^h$, where V_0 is the coarse space and $\{V_i^h\}_{i=1}^N$ are the local subspaces. For the coarse space, V_0, we use the standard multiscale finite element basis functions as described in [5, 8], where, we allow the basis functions to be continuous inside each coarse element K, and discontinuous across ∂K. Below is the description of V_0.

We define our coarse space associated with $\mathcal{T}_H$ as follows

$$V_0 = span\{\phi_{p,K}, \text{ for all } x_p \in \mathcal{N}^H(K), \ \forall K \in \mathcal{T}_H\}, \tag{3.1}$$

where $\mathcal{N}^H(K)$ includes all the vertex nodes of K, and $\phi_{p,K}$ denotes the multiscale basis function defined in (3.3). To be more specific, we need to introduce suitable boundary data $\psi_{p,\partial K}$, which is required to be piecewise linear(w.r.t. the given fine mesh $\mathcal{T}_h$ restricted to ∂K), and to satisfy the following: $\psi_{p,\partial K}(x_p'^H) = \delta_{p,p'}, \ \forall\ x_p, x_p' \in \mathcal{N}^H(K), \ 0 \le \psi_{p,\partial K}(x) \le 1,$ and $\sum_{x_p \in \mathcal{N}^H(K)} \psi_{p,\partial K}(x) = 1, \ \forall\ x \in \partial K,$ and $\psi_{p,\partial K}(x) = 0,$ on the edge of K opposite x_p.

An obvious choice for the boundary data $\psi_{p,\partial K}$ satisfying the above conditions is the standard linear boundary condition.

The linear boundary condition works well when the high conductivity regions lie strictly inside coarse grid blocks. However, when they touch the the coarse grid boundaries, linear boundary condition fails. In this case, we use another boundary condition, also known as oscillatory boundary condition, c.f., [5], which satisfies the above conditions and is effective. The description of this boundary condition is as follows:

Let Υ be an edge of the coarse mesh $\mathcal{T}_H$ with end points x_p and $x_{p'}$, and α^Υ be the restriction of α to Υ. Then the oscillatory boundary condition is given by the finite element solution of the following two-point boundary value problem:

$$-(\alpha^\Upsilon (\psi_p^\Upsilon)')' = 0, \ x \in \Upsilon$$

$$\psi_p^\Upsilon(x_p) = 1, \text{ and } \psi_p^\Upsilon(x_{p'}) = 0.$$

Since the coefficient α^Υ is piecewise constant, the finite element solution of the above equation can be expressed explicitly by

$$\psi_p^\Upsilon(x) = (\int_\Upsilon (\alpha^\Upsilon)^{-1} ds)^{-1} (\int_{\Upsilon_x} (\alpha^\Upsilon)^{-1} ds), \text{ for all } x \in \Upsilon, \tag{3.2}$$

where Υ_x denotes the line from $x_{p'}$ to x. The function ψ_p^Υ is continuous and piecewise linear with respect to $\Upsilon \cap \mathcal{T}_h$. We set $\psi_{p,\partial K} = \psi_p^\Upsilon$ on each edge Υ of K, containing x_p, and $\psi_{p,\partial K}|_\Upsilon = 0$ on the edge opposite to x_p.

Once the boundary condition $\psi_{p,\partial K}$ is determined, $\phi_{p,K}$ is constructed by a discrete harmonic extension inside K. First, define the P_1-conforming finite element space associated with $\mathcal{T}_h$ as

$$S^h(\Omega) = \{v : v|_\tau \text{ is linear and } v \text{ is a continous function over } \Omega\}.$$

Then $\phi_{p,K} \in S^h(K)$ can be defined as

$$\int_K \alpha \nabla \phi_{p,K} \cdot \nabla v_h = 0, \text{ for all } v_h \in S_0^h(K) \text{ subject to } \phi_{p,K}|_{\partial K} = \psi_{p,\partial K}, \tag{3.3}$$

where $S_0^h(K) = S^h(K) \cap H_0^1(K)$. The most important property of $\phi_{p,K}$ is the energy minimizing, which can be stated as follows,

$$|\phi_{p,K}|_{1,\alpha,K} \le |\theta|_{1,\alpha,K}, \text{ for all } \theta \in S^h(K) \text{ which satisfies } \theta|_{\partial K} = \phi_{p,K}|_{\partial K}. \tag{3.4}$$

Note that our coarse space V_0 actually includes functions which are required to be continuous inside each coarse element K and discontinuous across coarse grid boundaries, and obviously we have $V_0 \subset V^h$.

Having the above preparations, we may define $a_0(\cdot,\cdot)$ the bilinear form associated with V_0 as

$$\begin{aligned} a_0(u,v) =& \sum_K \int_K \alpha \nabla u \cdot \nabla v dx - \sum_{\substack{\partial K_{mk} \subset \Omega \\ m>k}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} \int_{e_{jl}} \{\alpha \nabla u\}_w^e [v] ds \\ & - \sum_{\substack{\partial K_{mk} \subset \Omega \\ m>k}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} \int_{e_{jl}} \{\alpha \nabla v\}_w^e [u] ds + \eta \sum_{\substack{\partial K_{mk} \subset \Omega \\ m>k}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} [u][v] ds \\ & - \sum_{\partial K \subset \partial \Omega} \sum_{e \subset \partial K} \int_e w_e \alpha_e \nabla u_e \cdot v_e \mathbf{n}_e ds - \sum_{\partial K \subset \partial \Omega} \sum_{e \subset \partial K} \int_e w_e \alpha_e \nabla v_e \cdot u_e \mathbf{n}_e ds \\ & + \eta \sum_{\partial K \subset \partial \Omega} \sum_{e \subset \partial K} \int_e \frac{W_e}{h_e} u_e v_e ds, \ \forall u, v \in V_0. \end{aligned} \tag{3.5}$$

Note that $V_0 \subset V^h$, and $a_0(u,v) = a_h(u,v), \ \forall u,v \in V_0$, hence it follows from Lemma 2.1 that $a_0(v,v)$ is coercive on V_0.

Next, we define the local spaces, $\{V_i^h\}_{i=1}^N$ associated with subdomain partition $\{B_i\}_{i=1}^N$.

$$V_i^h = \{v \in V^h : v = 0 \text{ in } \Omega \backslash \overline{B_i}\}, \ i = 1 \cdots N, \tag{3.6}$$

where $B_i = \Omega_i$ for the nonoverlapping partition, and $B_i = \Omega_i'$ for the overlapping partition.

The corresponding local bilinear forms $a_i(u,v)$ can be defined as follows:

$$\begin{aligned} a_i(u,v) =& \sum_{\tau \subset B_i} \int_\tau \alpha \nabla u \cdot \nabla v dx - \sum_{\substack{e_{jl} \subset B_i \\ j>l}} \int_{e_{jl}} \{\alpha \nabla u\}_w^e [v] ds - \sum_{\substack{e_{jl} \subset B_i \\ j>l}} \int_{e_{jl}} \{\alpha \nabla v\}_w^e [u] ds \\ & + \eta \sum_{\substack{e_{jl} \subset B_i \\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} [u][v] ds - \sum_{\substack{e_{jl} \subset \Gamma_i \\ j>l}} \int_{e_{jl}} w_e \alpha_e \nabla u_e \cdot v_e \mathbf{n}_e ds \\ & - \sum_{\substack{e_{jl} \subset \Gamma_i \\ j>l}} \int_{e_{jl}} w_e \alpha_e \nabla v_e \cdot u_e \mathbf{n}_e ds + \eta \sum_{\substack{e_{jl} \subset \Gamma_i \\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} u_e v_e ds \\ & - \sum_{e \subset \Xi_i} \int_e w_e \alpha_e \nabla u_e \cdot v_e \mathbf{n}_e ds - \sum_{e \subset \Xi_i} \int_e w_e \alpha_e \nabla v_e \cdot u_e \mathbf{n}_e ds \\ & + \eta \sum_{e \subset \Xi_i} \int_e \frac{W_e}{h_e} u_e v_e ds, \ \forall u, \ v \in V_i^h, \end{aligned} \tag{3.7}$$

where $\Gamma_i = \partial B_i \backslash \partial \Omega, \Xi_i = \partial B_i \cap \partial \Omega$.

Note that $V_i^h \subset V^h$, and $a_i(u,v) = a_h(u,v), \ \forall u,v \in V_i^h$, hence it follows from Lemma 2.1 that $a_i(v,v)$ is coercive on V_i^h.

Remark 3.1. Note that the local bilinear form $a_i(\cdot,\cdot)$ on $V_i^h \times V_i^h$ is actually the restriction of $a_h(\cdot,\cdot)$ on $V_i^h \times V_i^h$. Thus, in the implementation of this method, after we build the global stiffness matrix A corresponding to the bilinear form $a_h(\cdot,\cdot)$, we can easily get the local stiffness matrix A_i corresponding to $a_i(\cdot,\cdot)$ by taking the *i-th* diagonal block of A.

With this preparation, the two level additive Schwarz domain decomposition method can be presented as follows.

For $1 \leq i \leq N$, we define the operators $T_i : V^h \to V_i^h$ by

$$a_i(T_i u, v) = a_h(u, v), \ \forall u \in V^h, \ v \in V_i^h,$$

and for $i = 0$, we define the operator T_0 by

$$a_0(T_0 u, v) = a_h(u, v), \ \forall u \in V^h, \ v \in V_0.$$

Clearly, each of these problems has a unique solution.

We define the additive operator as

$$T = T_0 + T_1 + \cdots + T_N,$$

and replace (2.9) by the operator equation

$$Tu_h = f_h, \tag{3.8}$$

where

$$f_h = \sum_{i=0}^{N} g_i \ \text{ with } \ g_i = T_i u_h,$$

and u_h is the solution of (2.9).

3.1 Analysis

In this section, we estimate the condition number of both the nonoverlapping and overlapping additive Schwarz method. We use the standard Schwarz framework [2, 12].

We will see that, for the nonoverlapping method, the condition number will depend on the two indicators $\gamma(\alpha)$ and $\beta(\alpha)$, while for the overlapping method, it depends on an additional indicator $\pi(\alpha)$ which will be defined in Section 3.1.2.

The first indicator $\gamma(\alpha)$, which is borrowed from [5], measures the maximum weighted energy of all the coarse basis functions, which can be used to have an indication of how well the coarse basis functions are constructed. We will show that, by choosing suitable boundary conditions, $\gamma(\alpha)$ can be bounded independently of the jumps in the coefficients.

Coarse robustness indicator [5]. Given a coarse triangulation $\mathcal{T}_H$, and the set of coarse basis functions $\{\phi_{p,K}, \ \forall x_p \in \mathcal{N}^H(K), \ \forall K \in \mathcal{T}_H,\}$ then

$$\gamma(\alpha) = \max_{K \in \mathcal{T}_H} \max_{x_p \in \mathcal{N}^H(K)} |\phi_{p,K}|^2_{1,\alpha,K}.$$

Next, we introduce the indicator $\beta(\alpha)$, which measures the weighted L_2 norm of the jump of the multiscale basis functions on the coarse grid boundaries. It is the maximum value of $\beta^I(\alpha)$, which corresponds to the integration on the inner coarse grid boundaries that are inside Ω, and $\beta^B(\alpha)$, which corresponds to the integration on the coarse grid boundaries which intersect with $\partial\Omega$. The term $\beta(\alpha)$ enters into our analysis due to the use of the DG bilinear form on the coarse space.

Multiscale DG indicator. Given a coarse triangulation $\mathcal{T}_H$, and the set of coarse basis functions $\{\phi_{p,K}, \forall x_p \in \mathcal{N}^H(K),\ \forall K \in \mathcal{T}_H, \}$ then

$$\beta^I(\alpha) = \max_{\substack{\partial K_{mk} \subset \Omega \\ m>k}} \max_{\substack{x_p \in \mathcal{N}^H(K_m) \\ x_p \in \overline{\partial K_{mk}}}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} (\int_{e_{jl}} \frac{W_e}{h_e} |[\phi_p]|^2 ds). \tag{3.9}$$

where $[\phi_p] = \phi_{p,K_m} - \phi_{p,K_k}$, ∂K_{mk} is the edge shared by the coarse elements K_m and K_k, W_e is defined in (2.3), and h_e is the length of the edge e_{jl}.

However, when $\partial K_m \cap \partial\Omega \neq \emptyset$, we set

$$\beta^B(\alpha) = \max_{\partial K_m \subset \partial\Omega} \max_{\substack{x_p \in \mathcal{N}^H(K_m) \\ x_p \in \overline{\partial K_m}}} \sum_{e \subset \partial K_m} (\int_e \frac{W_e}{h_e} |\phi_{p,m}|^2 ds). \tag{3.10}$$

Having all the above preparations, we define

$$\beta(\alpha) = \max\big(\beta^I(\alpha), \beta^B(\alpha)\big). \tag{3.11}$$

3.1.1 Nonoverlapping additive Schwarz method

In this section, we propose a two level additive Schwarz method with nonoverlapping subdomains, and present an analysis of the condition number. Since it is a two level additive Schwarz method, we use V_0 in the previous section as our coarse space with bilinear form $a_0(\cdot,\cdot)$. For the local subspaces, by taking $B_i = \Omega_i$ in (3.6), we have

$$V_i^h = \{v \in V^h : v = 0 \text{ in } \Omega \backslash \overline{\Omega_i}\},\ i = 1 \cdots N.$$

Note that, in this case, V^h is a direct sum of $\{V_i^h\}$. The local forms $a_i(\cdot,\cdot)$, $1 \le i \le N$ are given by (3.7) with $B_i = \Omega_i$.

In order to estimate the condition number of the two level nonoverlapping domain decomposition method, we need to define an interface bilinear form, $I(\cdot,\cdot) : V^h \times V^h \to R$, as follows: $\forall u, v \in V^h$,

$$\begin{aligned} I(u,v) = -\sum_{\substack{\partial K_{mk} \\ m>k}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} \{ &\int_{e_{jl}} \alpha_j w_j \nabla u_j \cdot v_l \mathbf{n}_l ds + \int_{e_{jl}} \alpha_j w_j \nabla v_j \cdot u_l \mathbf{n}_l ds \\ &+ \int_{e_{jl}} \alpha_l w_l \nabla u_l \cdot v_j \mathbf{n}_j ds + \int_{e_{jl}} \alpha_l w_l \nabla v_l \cdot u_j \mathbf{n}_j ds \\ &+ \eta \int_{e_{jl}} \frac{W_e}{h_e} u_j v_l ds + \eta \int_{e_{jl}} \frac{W_e}{h_e} u_l v_j ds \}, \end{aligned} \tag{3.12}$$

where $u_j = u|_{\tau_j}$ and $u_l = u|_{\tau_l}$, with e_{jl} being the common edge between τ_j and τ_l.

Observe that the relationship between the bilinear form on the fine space and the bilinear forms on the local subspaces is given by

$$a_h(u,v) = \sum_{i=1}^N a_i(u_i, v_i) + I(u,v)\ \ \forall u, v \in V^h,\ u_i, v_i \in V_i^h, \tag{3.13}$$

where $u = \sum_{i=1}^N u_i$, and $v = \sum_{i=1}^N v_i$.

For the proof of (3.13), one only need to compare the terms in $a_h(u,v)$ with those in $\sum_{i=1}^N a_i(u_i, v_i)$,

$\forall u, v \in V^h,\ u_i, v_i \in V_i^h.$

The next lemma which states the Poincaré and a trace inequality for our discontinuous case, has been proved in [14].

Lemma 3.1. *Let D be a convex domain, $\{\mathcal{T}_D\}$ be a family of partitions of D, and $D = \bigcup_{\tau\in\mathcal{T}_D}\tau$ with $diam(\tau) \approx h$, then for any $u \in V_D = \Pi_{\tau\subset\mathcal{T}_D} H^1(\tau)$, with $\overline{u} = \frac{1}{|D|}\int_D u dx$ being the average value of u over D, we have*

$$\|u - \overline{u}\|_{0,D} \lesssim diam(D)|u|_{1,h,D},$$

where

$$|u|^2_{1,h,D} = \sum_{\tau\subset D}\|\nabla u\|^2_{0,\tau} + \sum_{\substack{e_{jl}\subset D\\ j>l}} h^{-1}\|[u]\|^2_{0,e_{jl}},$$

and $[u]$ denote the jump on the edge e_{jl}. Consequently, if $diam(D) \approx O(H)$, we have

$$||u||^2_{0,\partial D} \lesssim H^{-1}||u||^2_{0,D} + H|u|^2_{1,h,D}.$$

Remark 3.2. Note that, in the above Lemma, the condition on the convexity of the domain D is actually too strict. It is stated in [14] that this can be dropped.

Define the restriction operator $R_H : V^h(\Omega) \to V_0(\Omega)$ as follows:

$$R_H u(x_p) = \overline{u}_p,\ \forall u \in V^h(\Omega),\ \forall x_p \in \mathcal{N}^H(K),\ \forall K \in \mathcal{T}_H,$$

where $\overline{u}_p = \frac{1}{|\omega_p|}\int_{\omega_p} u dx$, with ω_p being the union of elements sharing x_p, as shown in the figure below.



Lemma 3.2. *For the restriction operator defined above, the following approximation and stability properties hold*

$$\|u - R_H u\|^2_{0,K} \le CH^2|u|^2_{1,h,\omega_K},\ \forall u \in V^h(\Omega).$$

$$a_0(R_H u, R_H u) \le C\max\big(\gamma(\alpha), \eta\beta(\alpha)\big)a_h(u,u),\ \forall u \in V^h(\Omega).$$

Particularly, if $\alpha(x) \equiv 1,\ \forall x \in \Omega$, and $\eta = 1$, then we have

$$a_0(R_H u, R_H u) \le C\max\big(\gamma(1), \beta(1)\big)a_h(u,u),\ \forall u \in V^h(\Omega),$$

where $\omega_K = \bigcup_{p\in\mathcal{N}^H(K)}\omega_p$, and the constant C is independent of h and H.

Proof. Since

$$\overline{u}_p = \frac{1}{|\omega_p|}\int_{\omega_p} u dx \le C\frac{1}{|\omega_p|}\|u\|_{0,\omega_p}|\omega_p|^{\frac{1}{2}} \le C\frac{1}{|\omega_p|^{\frac{1}{2}}}\|u\|_{0,\omega_p}, \tag{3.14}$$

we have

$$\begin{aligned}\|u-R_Hu\|_{0,K}^2 \leq & C\|u\|_{0,K}^2 + C\|R_Hu\|_{0,K}^2 \\ \leq & C\|u\|_{0,K}^2 + C\sum_{x_p\in\mathcal{N}^H(K)} \frac{1}{|\omega_p|}\|u\|_{0,\omega_p}^2 \leq C\|u\|_{0,K}^2 + C\frac{1}{|K|}\|u\|_{0,\omega_K}^2,\end{aligned}$$

where in the last inequality we have used $|\omega_p| > |K|$ and ω_p is part of ω_K.

Since our interpolation operator R_H keeps constants unchanged, we can take $u - \frac{1}{|\omega_K|}\int_{\omega_K} udx$ instead of u, and the approximation property holds due to the Poincaré inequality in Lemma 3.1.

Next, we prove the stability property. Let

$$\begin{aligned}a_0(R_Hu, R_Hu) = & \sum_K \int \alpha\nabla R_Hu\cdot\nabla R_Hudx \\ & - 2\sum_{\substack{\partial K_{mk}\subset\Omega \\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk} \\ j>l}} \int_{e_{jl}} \{\alpha\nabla R_Hu\}_w^e[R_Hu]ds \\ & + \eta\sum_{\substack{\partial K_{mk}\subset\Omega \\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk} \\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e}[R_Hu][R_Hu]ds \\ & - 2\sum_{\partial K\subset\partial\Omega}\sum_{e\subset\partial K}\int_e w_e\alpha_e\nabla(R_Hu)_e\cdot(R_Hu)_e\mathbf{n}_eds \\ & + \eta\sum_{\partial K\subset\partial\Omega}\sum_{e\subset\partial K}\int_e \frac{W_e}{h_e}(R_Hu)_e(R_Hu)_eds \\ = & I_1 - 2I_2 + I_3 - 2I_4 + I_5.\end{aligned}$$

We begin by estimating the term I_1. For each $K\in\mathcal{T}_H$, with $\widehat{u} = u - \frac{1}{|\omega_K|}\int_{\omega_K} udx$, it follows from the Poincaré inequality in Lemma 3.1 that

$$\begin{aligned}|R_Hu|_{1,\alpha,K}^2 = |R_H\widehat{u}|_{1,\alpha,K}^2 \lesssim & \sum_{x_p\in\mathcal{N}^H(K)} (|\omega_p|^{-1}||\widehat{u}||_{0,\omega_p}^2)|\phi_{p,K}|_{1,\alpha,K}^2 \\ \lesssim & \gamma(\alpha)|K|^{-1}||\widehat{u}||_{0,\omega_K}^2 \lesssim \gamma(\alpha)|u|_{1,h,\omega_K}^2.\end{aligned}$$

Summing over the elements $K\in\mathcal{T}_H$, we get

$$I_1 \lesssim \gamma(\alpha)\sum_K |u|_{1,h,\omega_K}^2 \lesssim \gamma(\alpha)a_h(u,u). \tag{3.15}$$

Next, we estimate the term I_2. Let $v = R_H u$, then by the Cauchy-Schwarz inequality

$$
\begin{aligned}
|I_2| &= \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \{\alpha\nabla v\}_w^e [v] ds \\
&\lesssim \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} (\int_{e_{jl}} |\{\alpha\nabla v\}_w^e|^2 ds)^{1/2} (\int_{e_{jl}} |[v]|^2 ds)^{1/2} \\
&\lesssim \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} (\int_{e_{jl}} \frac{h_e}{W_e} |\{\alpha\nabla v\}_w^e|^2 ds) + \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} |[v]|^2 ds.
\end{aligned}
$$

From the definition of $\{\cdot\}_w^e$, and (2.4), we have

$$
\begin{aligned}
|I_2| &\lesssim \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} (\int_{e_{jl}} \frac{h_e}{W_e} |w_-^e \alpha_-^e \nabla v_-^e + w_+^e \alpha_+^e \nabla v_+^e|^2 ds) \\
&\quad + \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} |[v]|^2 ds \\
&\lesssim \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} (\int_{e_{jl}} h_e \max(\frac{(w_-^e)^2 \alpha_-^e}{W_e}, \frac{(w_+^e)^2 \alpha_+^e}{W_e})(\alpha_-^e |\nabla v_-^e|^2 + \alpha_+^e |\nabla v_+^e|^2) ds) \\
&\quad + \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} |[v]|^2 ds \\
&\lesssim \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} (\int_{e_{jl}} h_e \alpha_-^e |\nabla v_-^e|^2 ds + \int_{e_{jl}} h_e \alpha_+^e |\nabla v_+^e|^2 ds) \\
&\quad + \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} |[v]|^2 ds.
\end{aligned}
$$

Let τ_+^e and τ_-^e be the two fine elements sharing the edge e, and note that ∇v_+^e and ∇v_-^e are constants on τ_+^e and τ_-^e respectively. Then

$$
\begin{aligned}
|I_2| &\lesssim \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} (\int_{\tau_-^e} \alpha_-^e |\nabla v_-^e|^2 ds + \int_{\tau_+^e} \alpha_+^e |\nabla v_+^e|^2 ds) \\
&\quad + \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} |[v]|^2 ds \\
&\lesssim \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} (\int_{\tau_+^e \cup \tau_-^e} |\alpha^{1/2} \nabla v|^2 dx) + \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} |[v]|^2 ds \\
&\lesssim \sum_K \int_K |\alpha^{1/2} \nabla R_H u|^2 dx + \sum_{\substack{\partial K_{mk}\subset\Omega\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e} |[R_H u]|^2 ds \lesssim I_1 + I_3.
\end{aligned}
\tag{3.16}
$$

We now consider the term I_3. First we note that, for all $\partial K_{mk},\ m > k$, we have

$$
\begin{aligned}
&\eta \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_e \frac{W_e}{h_e}|[R_H u]|^2 ds \\
\lesssim&\eta \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \sum_{\substack{x_p\in\mathcal{N}^H(K_m)\\ x_p\in\overline{\partial K_{mk}}}} \int_{e_{jl}} \frac{W_e}{h_e}|[\overline{u}_p\phi_p]|^2 ds \lesssim \eta\beta(\alpha) \sum_{\substack{x_p\in\mathcal{N}^H(K_m)\\ x_p\in\overline{\partial K_{mk}}}} |\overline{u}_p|^2 \\
\lesssim&\eta\beta^I(\alpha) \sum_{\substack{x_p\in\mathcal{N}^H(K_m)\\ x_p\in\overline{\partial K_{mk}}}} \frac{1}{|\omega_p|}||u||^2_{0,\omega_p} \lesssim \eta\beta^I(\alpha)\frac{1}{|K_m|}||u||^2_{0,\omega_{K_m}}.
\end{aligned}
$$

Taking $\widehat{u} = u - \frac{1}{|\omega_{K_m}|}\int_{\omega_{K_m}} udx$ instead of u in the above equation, it follows from the Poincaré inequality in Lemma 3.1 that

$$
\begin{aligned}
\eta \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e}|[R_H u]|^2 ds =&\eta \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e}|[R_H \widehat{u}]|^2 ds \\
\lesssim&\eta\beta^I(\alpha)\frac{1}{|K_m|}||\widehat{u}||^2_{0,\omega_{K_m}} \lesssim \eta\beta^I(\alpha)|u|^2_{1,h,\omega_{K_m}}.
\end{aligned}
$$

Hence, we have

$$
I_3 = \eta \sum_{\substack{\partial K_{mk}\\ m>k}} \sum_{e_{jl}\subset\partial K_{mk}} \int_{e_{jl}} \frac{W_e}{h_e}|[R_H u]|^2 ds \lesssim \eta\beta^I(\alpha)\sum_m |u|^2_{1,h,\omega_{K_m}} \lesssim \eta\beta^I(\alpha)a_h(u,u). \tag{3.17}
$$

Finally, for the terms on the boundary $\partial\Omega$, we apply the same techniques, and we get

$$
|I_4| \lesssim I_1 + I_5, \tag{3.18}
$$

and

$$
\begin{aligned}
I_5 = \eta \sum_{\partial K\subset\partial\Omega} \sum_{e\subset\partial K} \int_e \frac{W_e}{h_e}(R_H u)_e (R_H u)_e ds \lesssim&\eta\beta^B(\alpha)\sum_m |u|^2_{1,h,\omega_{K_m}} \\
\lesssim&\eta\beta^B(\alpha)a_h(u,u).
\end{aligned} \tag{3.19}
$$

The stability estimate for the general case thus follows from (3.15), (3.16), (3.17), (3.18) and (3.19) above. The estimate for the particular case holds naturally. □

We can now give an explicit bound for the condition number of our two level nonoverlapping additive Schwarz method.

Theorem 3.1. *For all $u \in V^h$, there exists $u_0 \in V_0$ and $u_i \in V_i^h$, $1 \le i \le N$, such that*

$$
\sum_{i=0}^N a_i(u_i, u_i) \le C\lambda a_h(u,u).
$$

Consequently, we have $\kappa(T) \lesssim \lambda$, where $\kappa(T)$ denotes the condition number of the additive Schwarz *operator T as defined in (3.8), and λ is given as*

$$\lambda = \eta \max_{\substack{\partial K_{mk} \\ m>k}} \max_{e \subset \partial K_{mk}} W_e \gamma(1) \frac{H}{h} + \max\big(\gamma(\alpha), \eta\beta(\alpha)\big),$$

where C is a constant independent of h, H, and α.

Proof. We need to verify the three assumptions of the Schwarz framework [2, 12]. More precisely, we need to estimate the three constants C_0^2, $\rho(M)$ and ω which corresponds to the three assumptions. The bound of the condition number is then given as:

$$\kappa(T) \le C_0^2 \omega(\rho(M) + 1).$$

The first assumption of the Schwarz framework, asks for an estimate of the smallest C_0^2 such that

$$\sum_{i=0}^{N} a_i(u_i, u_i) \lesssim C_0^2 a_h(u, u).$$

For all $u \in V^h$, let $u_0 = R_H u$, $z = u - u_0$ and $u_i = z|_{\Omega_i}$. From (3.13), we know that

$$a_h(u - u_0, u - u_0) = \sum_{i=1}^{N} a_i(u_i, u_i) + I(u - u_0, u - u_0).$$

Hence,

$$\begin{aligned} |\sum_{i=1}^{N} a_i(u_i, u_i)| &\le |a_h(u - u_0, u - u_0) - I(u - u_0, u - u_0)| \\ &\le |a_h(u - u_0, u - u_0)| + |I(u - u_0, u - u_0)| = I_1 + I_2. \end{aligned} \tag{3.20}$$

Using the fact that $a_h(u_0, u_0) = a_0(u_0, u_0)$ and Lemma 3.2, it then follows

$$I_1 = |a_h(u - u_0, u - u_0)| \lesssim a_h(u, u) + a_0(u_0, u_0) \lesssim \max\big(\gamma(\alpha), \eta\beta(\alpha)\big) a_h(u, u). \tag{3.21}$$

Next, we estimate the term I_2.

$$\begin{aligned} I_2 = |I(z, z)| \lesssim & \sum_{\substack{\partial K_{mk} \\ m>k}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} |\int_{e_{jl}} \alpha_j w_j \nabla z_j \cdot z_l \mathbf{n}_l ds| \\ & + \sum_{\substack{\partial K_{mk} \\ m>k}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} |\int_{e_{jl}} \alpha_l w_l \nabla z_l \cdot z_j \mathbf{n}_j ds| \\ & + \eta \sum_{\substack{\partial K_{mk} \\ m>k}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} |\int_{e_{jl}} \frac{W_e}{h_e} z_j z_l ds| = I_{21} + I_{22} + I_{23}. \end{aligned} \tag{3.22}$$

To estimate the terms I_{21} and I_{22}, we use similar techniques as in Lemma 3.2, which gives

$$I_{21} \lesssim \sum_{K} ||\alpha^{1/2}\nabla z||^2_{0,K} + \sum_{\substack{\partial K_{mk}\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \frac{W_e}{h_e}(\int_{e_{jl}} |z_l|^2 ds) = I_{211} + I_{212}, \tag{3.23}$$

and

$$I_{22} \lesssim \sum_{K} ||\alpha^{1/2}\nabla z||^2_{0,K} + \sum_{\substack{\partial K_{mk}\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \frac{W_e}{h_e}(\int_{e_{jl}} |z_j|^2 ds) = I_{221} + I_{222}. \tag{3.24}$$

Using the Cauchy-Schwarz inequality for the term I_{23}, we have

$$\begin{aligned} I_{23} =& \eta \sum_{\substack{\partial K_{mk}\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} |\int_{e_{jl}} \frac{W_e}{h_e} z_j z_l ds\}| \\ \lesssim& \eta \sum_{\substack{\partial K_{mk}\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} (\int_{e_{jl}} \frac{W_e}{h_e}|z_j|^2 ds)^{1/2}(\int_{e_{jl}} \frac{W_e}{h_e}|z_l|^2 ds)^{1/2} \\ \lesssim& \eta \sum_{\substack{\partial K_{mk}\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e}|z_j|^2 ds + \eta \sum_{\substack{\partial K_{mk}\\ m>k}} \sum_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e}|z_l|^2 ds \\ =& I_{231} + I_{232}. \end{aligned} \tag{3.25}$$

So, we need to estimate the six terms I_{211}, I_{212}, I_{221}, I_{222}, I_{231}, I_{232}. We begin by estimating the terms I_{211} and I_{221}. We note that

$$\begin{aligned} |u-u_0|^2_{1,\alpha,K} \lesssim& |u|_{1,\alpha,K} + \sum_{x_p\in\mathcal{N}^H(K)} (|\omega_p|^{-1}||u||^2_{0,\omega_p})|\phi_{p,K}|^2_{1,\alpha,K} \\ \lesssim& |u|_{1,\alpha,K} + \gamma(\alpha)\frac{1}{|K|}||u||^2_{0,\omega_K}. \end{aligned} \tag{3.26}$$

Let $\widehat{u} = u - \frac{1}{|\omega_K|}\int_{\omega_K} u dx$ and $\widehat{u}_0 = R_H\widehat{u}$. Also note that $u - u_0 = \widehat{u} - \widehat{u}_0$ since R_H preserves constants. It follows from (3.26) and Lemma 3.1 that

$$|u-u_0|^2_{1,\alpha,K} = |\widehat{u}-\widehat{u}_0|^2_{1,\alpha,K} \lesssim |u|^2_{1,\alpha,K} + \gamma(\alpha)\frac{1}{|K|}||\widehat{u}||^2_{0,\omega_K} \lesssim \gamma(\alpha)|u|^2_{1,h,\alpha,\omega_K}.$$

We then have

$$I_{211} = I_{221} = \sum_{K} |u-u_0|^2_{1,\alpha,K} \lesssim \gamma(\alpha)|u|^2_{1,h,\alpha,\omega_K} \lesssim \gamma(\alpha)a_h(u,u).$$

Next, we estimate the term I_{232}. Estimates for the terms I_{212}, I_{222} and I_{231} are similar.

$$
\begin{aligned}
I_{232} \lesssim & \eta \sum_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} \frac{W_e}{h_e} \sum_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} \int_{e_{jl}} |z_l|^2 ds \\
\lesssim & \eta \sum_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} \frac{W_e}{h_e} (\|z_m\|^2_{0,\partial K_m} + \|z_k\|^2_{0,\partial K_k}).
\end{aligned}
\tag{3.27}
$$

Using the trace inequality in Lemma 3.1, we have

$$
\begin{aligned}
I_{232} \lesssim & \eta \sum_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} \frac{W_e}{h_e} (H^{-1}\|z_m\|^2_{0,K_m} + H|z_m|^2_{1,h,K_m}) \\
& + \eta \sum_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} \frac{W_e}{h_e} (H^{-1}\|z_k\|^2_{0,K_k} + H|z_k|^2_{1,h,K_k}) \\
\lesssim & \eta \sum_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} \frac{W_e}{h_e} (H^{-1}\|u-u_0\|^2_{0,K_m} + H|u-u_0|^2_{1,h,K_m}) \\
& + \eta \sum_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} \frac{W_e}{h_e} (H^{-1}\|u-u_0\|^2_{0,K_k} + H|u-u_0|^2_{1,h,K_k}).
\end{aligned}
\tag{3.28}
$$

We recall that u_0 is a continuous function on each $K \in \mathcal{T}_H$, which implies that

$$
\begin{aligned}
|u-u_0|^2_{1,h,K} \lesssim & |u|^2_{1,h,K} + |u_0|^2_{1,h,K} \lesssim |u|^2_{1,h,K} + |u_0|^2_{1,K} \\
\lesssim & |u|_{1,h,K} + \sum_{x_p \in \mathcal{N}^H(K)} (|\omega_p|^{-1}\|u\|^2_{0,\omega_p})|\phi_{p,K}|^2_{1,K} \\
\lesssim & |u|_{1,h,K} + \gamma(1)\frac{1}{|K|}\|u\|^2_{0,\omega_K}.
\end{aligned}
\tag{3.29}
$$

Again let $\widehat{u} = u - \frac{1}{|\omega_K|}\int_{\omega_K} u dx$ and $\widehat{u}_0 = R_H \widehat{u}$, and note that $u - u_0 = \widehat{u} - \widehat{u}_0$ (R_H preserves constants), we have from (3.29) that

$$
|u-u_0|^2_{1,h,K} = |\widehat{u}-\widehat{u}_0|^2_{1,h,K} \lesssim |u|^2_{1,h,K} + \gamma(1)\frac{1}{|K|}\|\widehat{u}\|^2_{0,\omega_K} \lesssim \gamma(1)|u|_{1,h,\omega_K}. \tag{3.30}
$$

Using the approximation property of R_H in Lemma 3.2, as well as (3.30), it follows from (3.28) that

$$
\begin{aligned}
I_{232} \lesssim & \eta \sum_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} \frac{W_e}{h_e} (H|u|^2_{1,h,\omega_{K_m}} + H\gamma(1)|u|^2_{1,h,\omega_{K_m}}) \\
& + \eta \sum_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} \frac{W_e}{h_e} (H|u|^2_{1,h,\omega_{K_k}} + H\gamma(1)|u|^2_{1,h,\omega_{K_k}}) \\
\lesssim & \eta \max_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl}\subset \partial K_{mk} \\ j>l}} W_e \gamma(1) \frac{H}{h} a_h(u,u).
\end{aligned}
$$

Having all the estimates of the terms I_{21}, I_{22} and I_{23} together in (3.22), we get

$$I_2 \lesssim \eta \max_{\substack{\partial K_{mk}\\ m>k}} \max_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} W_e\gamma(1)\frac{H}{h}a_h(u,u)+\gamma(\alpha)a_h(u,u).$$

Combing (3.20), the estimates for I_1 and I_2, and Lemma 3.2 we have

$$\sum_{i=0}^{N} a_i(u_i,u_i) \lesssim \Big(\eta \max_{\substack{\partial K_{mk}\\ m>k}} \max_{\substack{e_{jl}\subset\partial K_{mk}\\ j>l}} W_e\gamma(1)\frac{H}{h} + \max\big(\gamma(\alpha),\eta\beta(\alpha)\big)\Big)a_h(u,u).$$

The second assumption of the Schwarz framework, requires a bound for the spectral radius $\rho(M)$ of the $N\times N$ matrix M, whose elements M_{ij} are defined in terms of a strengthen Cauchy Schwarz inequality: let $0\le M_{ij}\le 1$ be the minimum values such that

$$|a_h(u_i,u_j)| \le M_{ij}a_h(u_i,u_i)^{\frac{1}{2}}a_h(u_j,u_j)^{\frac{1}{2}},$$

where $u_i\in V_i^h,\ u_j\in V_j^h,\ 1\le i,j\le N$.

Note that in our definitions above

$$|a_h(u_i,u_j)|=0,\ \text{if}\ \mathrm{meas}(\partial\Omega_{ij})=0,\ 1\le i,j\le N,$$

where $\partial\Omega_{ij}=\partial\Omega_i\cap\partial\Omega_j$. This is because, according to (2.7), all the terms become zero since functions u_i and u_j have no common support. For the remaining case we can take $M_{ij}=1$. It follows at once from Gershgorin's circle theorem that

$$\rho(M)\le N_c+1,$$

where N_c is the maximum number of subdomains adjacent to any subdomain.

The third assumption asks for ω such that

$$a_h(u_i,u_i)\le \omega a_i(u_i,u_i),\ \forall u_i\in V_i^h,,\ 0\le i\le N.$$

Since we use exact bilinear form for the subproblems, $\omega=1$.

Our theorem is proved since the analysis of the three assumptions is complete. □

3.1.2 Overlapping additive Schwarz method

In this section, we analyze the overlapping version of our additive Schwarz method. As will be shown in Theorem 3.2, the condition number bound is not only dependent on the indicators $\gamma(\alpha)$ and $\beta(\alpha)$ but also on the partition robustness indicator $\pi(\alpha)$ borrowed from [5], which describes the relationship between the subdomain overlap and the coefficients α. We can control this indicator by choosing a suitable overlap.

Given an overlapping partition $\{\Omega_i'\}$ with $\delta_i>0$, $i=1,\cdots,N$, let $\{\chi_i\}_{i=1}^N$ be the partition of unity subordinate to $\{\Omega_i'\}$, c.f., [7], for which the following property holds,

$$\chi_i(x)=1 \text{ and } \nabla\chi_i=0,\ \text{for all}\ x\in\Omega_i'^{o}=\{x\in\Omega_i': x\notin\overline{\Omega_j'}\ \text{for any}\ j\ne i\}. \tag{3.31}$$

Partition robustness indicator [5]. For a particular partition of unity $\{\chi_i\}$ subordinate to the covering $\{\Omega_i'\}$, let

$$\pi(\alpha,\{\chi_i\}) = \max_{i=1}^{N}\{\delta_i^2\|\alpha|\nabla\chi_i|^2\|_{L_\infty(\Omega)}\},$$

then the partition robustness indicator is defined as

$$\pi(\alpha) = \inf_{\{\chi_i\}\in\Pi(\{\Omega_i'\})} \pi(\alpha,\{\chi_i\}),$$

where $\Pi(\{\Omega_i'\})$ denote the set of all the partitions of unity $\{\chi_i\}$ subordinate to the cover $\{\Omega_i'\}$.

Following similarly as the nonoverlapping case, we use V_0 as the coarse space with bilinear form $a_0(\cdot,\cdot)$, the subspaces V_i^h and the local bilinear forms $a_i(\cdot,\cdot)$, $1 \le i \le N$, can be got by taking $B_i = \Omega_i'$ in (3.6) and (3.7) respectively.

The next lemma gives us an estimate on the boundary layer.

Lemma 3.3. *Let D be a convex domain with $\mathrm{diam}(D) = O(H)$, $\mathcal{T}_D$ be a family of partitions over D, and $D = \bigcup_{\tau\in\mathcal{T}_D}\overline{\tau}$ with $\mathrm{diam}(\tau) = O(h)$. Let $0 < \mu \le H$, then for any $u \in V_D = \Pi_{\tau\subset\mathcal{T}_D}H^1(\tau)$, then we have*

$$||u||_{0,D_\mu}^2 \le C[\mu H^{-1}||u||_{0,D}^2 + \mu(\mu+H)|u|_{1,h,D}^2],$$

where $D_\mu = \{x \in D : \mathrm{dist}(x,\partial D) \le \mu\}$ denotes the boundary layer of D with width μ, and $|u|_{1,h,D}^2 = \sum_{\tau\subset D}||\nabla u||_{0,\tau}^2 + \sum_{\substack{e_{jl}\subset D\\ j>l}} h_{jl}^{-1}\int_{e_{jl}}[u]^2 ds$.

The proof of this lemma can be found in [14], again the assumption on the convexity of the domain D can be dropped, c.f., [14].

Theorem 3.2. *For all $u \in V^h$, there exists $u_0 \in V_0$ and $u_i \in V_i^h$, $1 \le i \le N$, such that*

$$\sum_{i=0}^{N} a_i(u_i,u_i) \le C\lambda a_h(u,u),$$

Consequently, we have $\kappa(T) \lesssim \lambda$, where $\kappa(T)$ denotes the condition number of the additive Schwarz operator T as defined in (3.8), and λ is given as

$$\lambda = \pi(\alpha)\max\big(\gamma(1),\beta(1)\big)\max_i\frac{H_i}{\delta_i} + \max\big(\gamma(\alpha),\eta\beta(\alpha)\big),$$

and C is a constant independent of h, H, and α.

Proof. Again, we use the Schwarz framework to prove this theorem. Like in the nonoverlapping case, we estimate the three parameters C_0^2, $\rho(M)$ and ω .

We first estimate C_0^2. For all $u \in V^h$, we may choose $u_0 = R_H u$ and $u_i = I_h(\chi_i(u-u_0))$, where I_h is the usual Lagrange interpolation operator. Let $w = u - u_0$ and $\{\chi_i\}$ be the partition of unity subordinate to the covering $\{\Omega_i'\}$, then $u_i = I_h(\chi_i w)$.

For $1 \leq i \leq N$, since $\chi_i = 0$ on $\Gamma_i = \partial\Omega_i' \backslash \partial\Omega$, we know from (3.7) that

$$\begin{aligned} a_i(u_i, u_i) = &\sum_{\tau \subset \Omega_i'} \int_\tau \alpha \nabla u_i \cdot \nabla u_i dx - 2 \sum_{\substack{e_{jl} \subset \Omega_i' \\ j > l}} \int_{e_{jl}} \{\alpha \nabla u_i\}_w^e [u_i] ds \\ &+ \eta \sum_{\substack{e_{jl} \subset \Omega_i' \\ j > l}} \int_{e_{jl}} \frac{W_e}{h_e} [u_i][u_i] ds - 2 \sum_{e \subset \Xi_i} \int_e w_e \alpha_e (\nabla u_i)_e \cdot (u_i)_e \mathbf{n}_e ds \\ &+ \eta \sum_{e \subset \Xi_i} \int_e \frac{W_e}{h_e} (u_i)_e (u_i)_e ds. \end{aligned}$$

Using the same techniques as in Lemma 3.2, we can write

$$\sum_{\substack{e_{jl} \subset \Omega_i' \\ j > l}} \int_{e_{jl}} \{\alpha \nabla u_i\}_w^e [u_i] ds \lesssim \sum_{\tau \subset \Omega_i'} \int_\tau \alpha \nabla u_i \cdot \nabla u_i dx + \eta \sum_{\substack{e_{jl} \subset \Omega_i' \\ j > l}} \int_{e_{jl}} \frac{W_e}{h_e} [u_i]^2 ds,$$

and

$$\sum_{e \subset \Xi_i} \int_e w_e \alpha_e (\nabla u_i)_e \cdot (u_i)_e \mathbf{n}_e ds \lesssim \sum_{\tau \subset \Omega_i'} \int_\tau \alpha \nabla u_i \cdot \nabla u_i dx + \eta \sum_{e \subset \Xi_i} \int_e \frac{W_e}{h_e} (u_i)_e^2 ds.$$

Consequently,

$$\begin{aligned} a_i(u_i, u_i) \lesssim &\sum_{\tau \subset \Omega_i'} \int_\tau \alpha \nabla u_i \cdot \nabla u_i dx + \eta \sum_{\substack{e_{jl} \subset \Omega_i' \\ j > l}} \int_{e_{jl}} \frac{W_e}{h_e} [u_i]^2 ds + \eta \sum_{e \subset \Xi_i} \int_e \frac{W_e}{h_e} (u_i)_e^2 ds \\ =& I_1 + I_2 + I_3. \end{aligned}$$

We begin by estimating term I_1. Since $u_i = I_h(\chi_i w)$, we have

$$I_1 = \sum_{\tau \subset \Omega_i'} \int_\tau \alpha \nabla u_i \cdot \nabla u_i dx = \sum_{\tau \subset \Omega_i'} \int_\tau \alpha |\nabla I_h(\chi_i w)|^2 dx.$$

Let $\chi_{i,\tau} = \frac{1}{|\tau|} \int_\tau \chi_i dx$, then it follows from the Bramble-Hilbert Lemma, c.f., [7], that,

$$||\chi_i - \chi_{i,\tau}||_{0,\infty,\tau} \lesssim \begin{cases} h_\tau |\nabla \chi_i|, & \forall \tau \subset \Omega_{i,\delta_i}', \\ 0, & \tau \subset \Omega_i'^o, \end{cases}$$

where $\Omega_{i,\delta_i}' = \{x \in \Omega_i' : dist(x, \partial\Omega_i') \leq \delta_i\}$ denotes the boundary layer of Ω_i' with width δ_i, and $\Omega_i'^o = \Omega_i' \backslash \Omega_{i,\delta_i}'$ is the interior part of Ω_i'.

Since the interpolation operator I_h is stable with respect to the norm $||\cdot||_{0,\infty,\Omega}$, using the inverse inequality, we have

$$\begin{aligned}\int_\tau \alpha|\nabla I_h(\chi_i w)|^2 dx =&||\alpha^{1/2}\nabla(I_h(\chi_i w))||_{0,\tau}^2\\ \lesssim&||\alpha^{1/2}\nabla(I_h(\chi_{i,\tau} w))||_{0,\tau}^2+||\alpha^{1/2}\nabla I_h((\chi_i-\chi_{i,\tau})w)||_{0,\tau}^2\\ \lesssim&||\alpha^{1/2}\nabla w||_{0,\tau}^2+h_\tau^{-2}||\alpha^{1/2}I_h((\chi_i-\chi_{i,\tau})w)||_{0,\tau}^2\\ \lesssim&||\alpha^{1/2}\nabla w||_{0,\tau}^2+||\alpha^{1/2}I_h((\chi_i-\chi_{i,\tau})w)||_{0,\infty,\tau}^2\\ \lesssim&||\alpha^{1/2}\nabla w||_{0,\tau}^2+h_\tau^{-2}\alpha||\chi_i-\chi_{i,\tau}||_{0,\infty,\tau}^2||w||_{0,\tau}^2,\end{aligned}$$

which implies that

$$\int_\tau \alpha|\nabla I_h(\chi_i w)|^2 dx \lesssim ||\alpha^{1/2}\nabla w||_{0,\tau}^2+\begin{cases}\alpha|\nabla\chi_i|^2||w||_{0,\tau}^2, & \forall\tau\subset\Omega'_{i,\delta_i},\\ 0, & \tau\subset\Omega_i'^{o}.\end{cases}$$

Adding this estimate across all the fine elements $\tau\subset\Omega'_i$, we have

$$I_1=\sum_{\tau\subset\Omega'_i}\int_\tau \alpha\nabla I_h(\chi_i w)\cdot\nabla I_h(\chi_i w)dx\lesssim ||\alpha|\nabla\chi_i|^2||_{0,\infty,\Omega}||w||_{0,\Omega'_{i,\delta_i}}^2+|w|_{1,\alpha,\Omega'_i}^2.$$

By the definition of $\pi(\alpha)$, and using the estimate in Lemma 3.3 with $\mu=\delta_i$ and $D=\Omega'_i$, we have

$$\begin{aligned}I_1&\lesssim\pi(\alpha)\frac{1}{\delta_i^2}||w||_{0,\Omega'_{i,\delta_i}}^2+|w|_{1,\alpha,\Omega'_i}^2\\ &\lesssim\pi(\alpha)\frac{1}{\delta_i^2}(\delta_i H_i^{-1}||w||_{0,\Omega'_i}^2+\delta_i H_i|w|_{1,h,\Omega'_i}^2)+|w|_{1,\alpha,\Omega'_i}^2\\ &\lesssim\pi(\alpha)\delta_i^{-1}H_i^{-1}\sum_{K\cap\Omega'_i\neq\emptyset}||w||_{0,K}^2+\pi(\alpha)\frac{H_i}{\delta_i}|w|_{1,h,\Omega'_i}^2+|w|_{1,\alpha,\Omega'_i}^2 \qquad (3.32)\\ &\lesssim\pi(\alpha)\frac{H_i}{\delta_i}\sum_{K\cap\Omega'_i\neq\emptyset}|u|_{1,h,\omega_K}^2+\pi(\alpha)\frac{H_i}{\delta_i}|w|_{1,h,\Omega'_i}^2+|w|_{1,\alpha,\Omega'_i}^2,\end{aligned}$$

where in the last inequality we have used the approximation property of R_H from Lemma 3.2.

Next, we estimate the term I_2. We first note that

$$\begin{aligned}|[u_i]|_{0,e_{jl}}^2&=|u_i^j-u_i^l|_{0,e_{jl}}^2=|I_h(\chi_i w^j)-I_h(\chi_i w^l)|_{0,e_{jl}}^2\\ &=|I_h(\chi_i(w^j-w^l))|_{0,e_{jl}}^2\le|w_j-w_l|_{0,e_{jl}}^2=|[w]|_{0,e_{jl}}^2,\end{aligned}\qquad(3.33)$$

where in the above equality we have used $|\chi_i|\le 1,\ 1\le i\le N$, and the stability property of I_h w.r.t. the norm $||\cdot||_{0,\infty,\Omega}$.

It follows from (3.33) that

$$I_2=\eta\sum_{\substack{e_{jl}\subset\Omega'_i\\ j>l}}\int_{e_{jl}}\frac{W_e}{h_e}[u_i]^2ds\lesssim\eta\sum_{\substack{e_{jl}\subset\Omega'_i\\ j>l}}\int_{e_{jl}}\frac{W_e}{h_e}[w]^2ds.$$

Finally, for the term I_3, since, by definition, $u_i = I_h(\chi_i w)$ and $\chi_i = 1$ on Ξ_i, we have

$$I_3 = \eta \sum_{e\subset\Xi_i} \int_e \frac{W_e}{h_e}(u_i)_e^2 ds \lesssim \eta \sum_{e\subset\Xi_i} \int_e \frac{W_e}{h_e} w_e^2 ds.$$

Combining the estimates of I_1, I_2 and I_3, $1 \le i \le N$, we have

$$\begin{aligned}
\sum_{i=1}^N a_i(u_i,u_i) \lesssim & \sum_{i=1}^N \sum_{\tau\subset\Omega_i'} \int_\tau \alpha\nabla u_i\cdot\nabla u_i dx + \eta \sum_{i=1}^N \sum_{\substack{e_{jl}\subset\Omega_i' \\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e}[u_i]^2 ds \\
& + \eta \sum_{i=1}^N \sum_{e\subset\Xi_i} \int_e \frac{W_e}{h_e}(u_i)_e^2 ds \\
\lesssim & \sum_{i=1}^N \pi(\alpha)\frac{H_i}{\delta_i} \sum_{K\cap\Omega_i'\neq\emptyset} |u|_{1,h,\omega_K}^2 + \sum_{i=1}^N \pi(\alpha)\frac{H_i}{\delta_i}|w|_{1,h,\Omega_i'}^2 + \sum_{i=1}^N |w|_{1,\alpha,\Omega_i'}^2 \\
& + \eta \sum_{i=1}^N \sum_{\substack{e_{jl}\subset\Omega_i' \\ j>l}} \int_{e_{jl}} \frac{W_e}{h_e}[w]^2 ds + \eta \sum_{i=1}^N \sum_{e\subset\Xi_i} \int_e \frac{W_e}{h_e} w_e^2 ds \\
\lesssim & \pi(\alpha)\max_i \frac{H_i}{\delta_i} a_h(u,u) + \sum_{i=1}^N \pi(\alpha)\frac{H_i}{\delta_i}|u - R_H u|_{1,h,\Omega_i'}^2 + a_h(w,w).
\end{aligned} \tag{3.34}$$

Note that,

$$\sum_{i=1}^N \pi(\alpha)\frac{H_i}{\delta_i}|u - R_H u|_{1,h,\Omega_i'}^2 \lesssim \sum_{i=1}^N \pi(\alpha)\frac{H_i}{\delta_i}|u|_{1,h,\Omega_i'}^2 + \sum_{i=1}^N \pi(\alpha)\frac{H_i}{\delta_i}|R_H u|_{1,h,\Omega_i'}^2. \tag{3.35}$$

It follows from Lemma 3.2 that

$$\sum_{i=1}^N |R_H u|_{1,h,\Omega_i'}^2 \lesssim \max\big(\gamma(1),\beta(1)\big) a_h(u,u),$$

which, together with (3.35), implies that

$$\sum_{i=1}^N \pi(\alpha)\frac{H_i}{\delta_i}|u - R_H u|_{1,h,\Omega_i'}^2 \lesssim \pi(\alpha)\max_i \frac{H_i}{\delta_i} \max\big(\gamma(1),\beta(1)\big) a_h(u,u).$$

Since $u_0 = R_H u$, using the stability property of $R_H u$ in Lemma 3.2, we have

$$\begin{aligned}
a_h(w,w) =& a_h(u-u_0, u-u_0) \lesssim a_h(u,u) + a_h(u_0,u_0) \\
\lesssim & \max\big(\gamma(\alpha),\eta\beta(\alpha)\big) a_h(u,u).
\end{aligned}$$

Thus, by (3.34), we have

$$\sum_{i=1}^N a_i(u_i,u_i) \lesssim \pi(\alpha)\max_i \frac{H_i}{\delta_i} \max\big(\gamma(1),\beta(1)\big) + \max\big(\gamma(\alpha),\eta\beta(\alpha)\big) a_h(u,u).$$

Note that $a_0(R_H u, R_H u) \lesssim \max\big(\gamma(\alpha), \eta\beta(\alpha)\big) a_h(u,u)$, which implies that

$$C_0^2 \lesssim \pi(\alpha) \max\big(\gamma(1), \beta(1)\big) \max_i \frac{H_i}{\delta_i} + \max\big(\gamma(\alpha), \eta\beta(\alpha)\big).$$

The other two parameters $\rho(M)$ and ω are estimated in the same way as before. $\square$

3.2 Oscillatory boundary conditions

In this section, we follow the notations used in [5], and give an explicit bound for the indicator $\gamma(\alpha)$ with a slightly different proof. We show that if the high-conductivity region crosses the boundaries of coarse grid blocks, the coarse basis function with linear boundary condition fails to give a robust bound for the condition number. The coarse basis functions with oscillatory boundary condition, on the other hand, yield a robust method. First, for each $K \in \mathcal{T}_H$, let $\rho \geq 1$ be an arbitrary constant, define the set

$$K(\rho) := \{x \in K, \alpha(x) > \rho\}.$$

Since $\alpha(x)$ is piecewise constant with respect to $\mathcal{T}_h$, $K(\rho)$ is a union of fine grid elements. Let the region

$$K(\rho) = K^I(\rho) \cup K^B(\rho)$$

be associated with each $K \in \mathcal{T}_H$, where the set $K^B(\rho)$ contains the components of $K(\rho)$ whose closure touches ∂K and $K^I(\rho)$ contains all the interior components of $K(\rho)$. The term $\varepsilon(\rho, K)$, representing the distance between $K^I(\rho)$ and $K^B(\rho)$, be defined as

$$\varepsilon(\rho, K) = \mathrm{dist}(K^I(\rho), K^B(\rho)).$$

Assumption 3.1. (1) $K^I(\rho)$ and $K^B(\rho)$ should be well-separated, i.e.,

$$\varepsilon(\rho, K) \geq h.$$

(2) $K^B(\rho)$ can be written as a union $K^B(\rho) = \sum_{l=1}^{L} K_l^B(\rho)$, where the components $K_l^B(\rho)$ are simply connected and pairwise disjoint, and $\alpha(x)$ is a constant on the closure of each component, i.e.,

$$\alpha(x) = \alpha_l, \text{ for all } x \in \overline{K_l^B(\rho)}.$$

(3) Let $\Gamma_l^B(\rho) = K_l^B(\rho) \cap \partial K$ be the boundary part of ∂K which locates in $K_l^B(\rho)$, and that $\Gamma^B(\rho) = \sum_{l=1}^{L} \Gamma_l^B(\rho)$. For all $K \in \mathcal{T}_H$, let E be any edge of ∂K, we require that

$$|E \backslash \Gamma^B(\rho)| \gtrsim H_K,$$

which means that the high conductivity field does not cover too much of ∂K, $\forall K \in \mathcal{T}_H$.

Note that, our assumptions are weaker than those [5], we do not need the coefficient $\alpha(x)$ to be continuous across the coarse grid boundaries. Next we give the explicit bound for the indicator $\gamma(\alpha)$ in Theorem 3.3 with a different proof than in [5].

Theorem 3.3. *Let Assumption 3.1 hold true for each $K \in \mathcal{T}_H$, then an upper bound for the* *indicator $\gamma(\alpha)$, with $\psi_{p,\partial K}$ being the oscillatory boundary condition, is given by*

$$\gamma(\alpha) \lesssim \rho \frac{H}{h}.$$

Proof. The key idea is to partition $K(\rho)$ into two parts $K_1(\rho)$ and $K_2(\rho)$, c.f., Figure 1, build a special function $\theta \in S^h(K)$ whose bound can be estimated.



Figure 1: The areas surrounded by dashed lines are $K^B(\rho)$ and $K^I(\rho)$ respectively. $K_1(\rho)$ and $K_2(\rho)$ are separated by dotted lines.

Let $K \in \mathcal{T}_H$, and $\psi_{p,\partial K}$ be the oscillatory boundary condition, $\phi_{p,K}$ is the multiscale basis function which is built through the discrete harmonic extension, c.f., (3.3). Accordingly,

$$|\phi_{p,K}|_{1,\alpha,K} \leq |\theta|_{1,\alpha,K}, \text{ for all } \theta \in S^h(K) \text{ which satisfies } \theta|_{\partial K} = \phi_{p,K}|_{\partial K}.$$

We only need to construct a function θ for which we can estimate its $|\cdot|_{1,\alpha,K}$ norm. We define the function θ explicitly by its values at the nodes of $\mathcal{N}^h(\overline{K})$, where $\mathcal{N}^h(\overline{K})$ denotes the set of fine mesh vertexes in $\overline{K}$. Obviously, the function θ is contained in $S^h(K)$. We begin by constructing θ on each $K^B(\rho)$. By Assumption 3.1, $K^B(\rho) = \sum_{l=1}^L K_l^B(\rho)$ and that $\Gamma^B(\rho) = \sum_{l=1}^L \Gamma_l^B(\rho)$ with $\Gamma_l^B = K_l^B(\rho) \cap \partial K$ being the part of ∂K locating in $K_l^B(\rho)$. Next, we define the values of θ on $\Gamma_l^B(\rho)$, then extend to $K_l^B(\rho)$, $\forall\ 1 \leq l \leq L$. For simplicity, we assume that Γ_l^B lies only in the interior of ∂K, i.e., $\overline{\Gamma_l^B}$ does not touch any vertex of K. For a fixed l, we may choose local coordinate system (x_1, x_2) and some $b_1, b_2 > 0$ such that $K \subset \{(x_1, x_2) : x_2 \geq 0\}$, $\Gamma_l^B = \{(x_1, 0) : x_1 \in [b_1, b_2]\}$. Define $\theta(x_1, x_2) = \psi(x_1, 0)$ for all $(x_1, x_2) \in K_l^B(\rho)$. After defining all the values of θ on $K^B(\rho)$, its values at the nodes of $K \backslash \overline{K^B(\rho)}$ for which we set 0.

Define

$$K_1(\rho) = \{x \in K : \operatorname{dist}(x, \partial K) \leq d\},$$

where $d = \max_{x \in \overline{K^B(\rho)}} \operatorname{dist}(x, \partial K)$. Similarly, $K_2(\rho) = K \backslash \overline{K_1(\rho)}$ denote the area of K which is not contained in $K_1(\rho)$. Clearly, $K^B(\rho) \subset K_1(\rho)$ and $K^I(\rho) \subset K_2(\rho)$ hold by their definitions.

We give an upper bound for $|\theta|_{1,\alpha,K}^2$. We note,

$$|\theta|_{1,\alpha,K}^2 \leq |\theta|_{1,\alpha,K_1(\rho)}^2 + |\theta|_{1,\alpha,K_2(\rho)}^2 = I_1 + I_2.$$

For the term I_1, we have

$$I_1 = |\theta|^2_{1,\alpha,K_1(\rho)} = |\theta|^2_{1,\alpha,K^B(\rho)} + |\theta|^2_{1,\alpha,K_1(\rho)\backslash K^B(\rho)} = I_{11} + I_{12}.$$

From (3.2) and the nodal values defined above we can see that $(\frac{\partial\theta}{\partial x_1})^2+(\frac{\partial\theta}{\partial x_2})^2 = \alpha^{-2}/\big(\int_\Upsilon(\alpha^\Upsilon)^{-1}ds\big)^2$ on each $\tau \subset K^B(\rho)$, where $\Upsilon \cap K^B(\rho) \neq \emptyset$ is the coarse edge of K. Hence

$$I_{11} = \sum_{\tau\in K^B(\rho)} \int_\tau \alpha((\frac{\partial\theta}{\partial x})^2 + (\frac{\partial\theta}{\partial y}))^2 dx_1dx_2 = \sum_{\tau\in K^B(\rho)} \int_\tau \alpha^{-1}/\big(\int_\Upsilon(\alpha^\Upsilon)^{-1}ds\big)^2 dx_1dx_2.$$

Let $\Upsilon_1 = \Upsilon\cap K^B(\rho)$ and $\Upsilon_2 = \Upsilon\backslash K^B(\rho)$, since $(\alpha^\Upsilon)^{-1} \geq \rho^{-1}$ on Υ_2, it follows from Assumption 3.1 (3) that

$$\int_\Upsilon(\alpha^\Upsilon)^{-1}ds = \int_{\Upsilon_1}(\alpha^\Upsilon)^{-1}ds + \int_{\Upsilon_2}(\alpha^\Upsilon)^{-1}ds > \int_{\Upsilon_2}(\alpha^\Upsilon)^{-1}ds \gtrsim \rho^{-1}|\Upsilon_2| \gtrsim \rho^{-1}H_K,$$

which implies that

$$I_{11} = \sum_{\tau\in K^B(\rho)} \int_\tau \alpha^{-1}/\big(\int_\Upsilon(\alpha^\Upsilon)^{-1}ds\big)^2 dx_1dx_2 \lesssim \sum_{\tau\in K^B(\rho)} \rho^{-1}|\tau|/\rho^{-2}H_K^2 \lesssim \rho.$$

For the term I_{12}, let $K_3(\rho) = K_1(\rho)\backslash\overline{K^B(\rho)}$, and

$$K_3(\rho_h) = \{\tau \subset K_3(\rho) : \overline{\tau} \cap \partial K_3(\rho) \neq \emptyset\}$$

be the boundary layer of $K_3(\rho)$ with width h. Note that, by definition, we have $\nabla\theta = 0$ on $K_3(\rho)\backslash K_3(\rho_h) = \{\tau \subset K_3(\rho) : \overline{\tau}\cap\partial K_3(\rho) = \emptyset\}$, and since $\alpha \leq \rho$ on $K_3(\rho)$, we get

$$I_{12} = |\theta|^2_{1,\alpha,K_3(\rho)} = \sum_{\tau\in K_3(\rho)} |\theta|^2_{1,\alpha,\tau} = \sum_{\tau\in K_3(\rho_h)} |\theta|^2_{1,\alpha,\tau} \lesssim \rho \sum_{\tau\in K_3(\rho_h)} |\theta|^2_{1,\tau} \lesssim \rho\frac{H}{h},$$

where in the last inequality we have used the fact that $|\theta|^2_{1,\tau} \lesssim 1$ since all the nodal values of θ defined on τ are between 0 and 1.

Finally, for the term I_2, define

$$K_2^B(\rho) = \{\tau \subset K_2(\rho) : \overline{\tau} \cap \partial K_2(\rho) \neq \emptyset\},$$

which is the boundary layer of width h of $K_2(\rho)$, and

$$K_2^I(\rho) = K_2(\rho)\backslash K_2^B(\rho),$$

which is the interior part of $K_2(\rho)$.

By the definition of θ, we have $\theta(x) = 0$ on $K_2^I(\rho)$. Since $\alpha \leq \rho$ on $K_2^B(\rho)$, we get

$$I_2 = |\theta|^2_{1,\alpha,K_2(\rho)} = \sum_{\tau\subset K_2^B(\rho)} |\theta|^2_{1,\alpha,\tau} \leq \rho \sum_{\tau\subset K_2^B(\rho)} |\theta|^2_{1,\tau} \leq \rho\frac{H}{h}.$$

The theorem is proved by combining the upper bounds for I_1 and I_2 together. $\square$

3.3 Upper bound of DG indicator

In this section, we estimate the term $\beta(\alpha)$. Note that, if the coefficient field is continuous across the coarse grid boundaries, we have $\beta^I(\alpha) = 0$, thus in this case, what we need to focus on is the estimate of the term $\beta^B(\alpha)$. However, in reality, the coefficient field can be discontinuous across the coarse grid boundaries. In both cases, suppose the coefficient of the conductivity field satisfies $W_e \lesssim \rho$, where $\rho \geq 1$ is a given number, on the edges of fine mesh triangles which intersect with the coarse grid boundaries. Then the indicator $\beta(\alpha)$ yield a bound which is independent of the high contrast in the coefficients.

Theorem 3.4. *For all $K \in \mathcal{T}_H$, $e \subset \partial K$, let the coefficient field be discontinuous across the coarse grid boundaries. If there exists $\rho > 0$ such that $W_e \lesssim \rho$, then*

$$\beta(\alpha) \lesssim \rho \frac{H}{h}.$$

Proof. By definition, c.f., (3.9), we have

$$\begin{aligned}
\beta^I(\alpha) &= \max_{\substack{\partial K_{mk} \subset \Omega \\ m>k}} \max_{\substack{x_p \in \mathcal{N}^H(K_m) \\ x_p \in \overline{\partial K_{mk}}}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} \left(\int_e \frac{W_e}{h_e} |[\phi_p]|^2 ds \right) \\
&\lesssim \max_{\substack{\partial K_{mk} \subset \Omega \\ m>k}} \max_{\substack{x_p \in \mathcal{N}^H(K_m) \\ x_p \in \overline{\partial K_{mk}}}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} \left(\int_e \frac{\rho}{h_e} |[\phi_p]|^2 ds \right) \\
&\lesssim \max_{\substack{\partial K_{mk} \subset \Omega \\ m>k}} \max_{\substack{x_p \in \mathcal{N}^H(K_m) \\ x_p \in \overline{\partial K_{mk}}}} \sum_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} \left(\int_e \frac{\rho}{h_e} 1^2 ds \right) \lesssim \rho \frac{H}{h},
\end{aligned}$$

using the fact that $|[\phi_p]| \lesssim 1$. The same result holds for the estimate on $\beta^B(\alpha)$. Hence, since $\beta(\alpha) = \max\left(\beta^I(\alpha), \beta^B(\alpha)\right)$, the theorem is proved. ☐

4 Numerical Experiments

In this section, we present our numerical results, where we solve the equation (2.1, 2.2) with $g = 0$ on the square domain $\Omega = [0,1]^2$. We run the preconditioned conjugate gradient method until the l_2 norm of the residual is reduced by a factor of 10^6.

In the numerical experiments, subdomains $\{\Omega_i\}_{i=1}^N$ are all square shaped, and each subdomain consists of two coarse triangles. In each of our numerical experiments below, we consider the performance of our two methods and compare with the method in [5]. The results of our method are shown in the columns under the heading "Discontinuous Galerkin", while the results from [5] are shown under the heading "Continuous Galerkin". We also use different basis functions for the coarse space, ϕ_p^L, $\phi_p^{MS,L}$, and $\phi_p^{MS,OSC}$, that is, the piecewise linear basis function, the multiscale basis function with linear boundary condition, and the multiscale basis function with oscillatory boundary condition, respectively. We choose the same penalty parameter η for both the fine and coarse bilinear forms.

Example 4.1. We begin with our first example here, see Figure 2, where $H \geq 8h$ and $\alpha(x)$ denotes a 'binary' medium with $\alpha(x) = \widehat{\alpha}$ on a square area inclusion lying in the middle of each coarse grid element $K \in \mathcal{T}_H$, and at a distance of $H/8$ both from the horizontal and the vertical edge of K,



Figure 2: The coefficient $\alpha(x)$ corresponding to the binary domain of Example 4.1.

and $\alpha(x) = 1$ in the rest of the domain. We study the behavior of the preconditioners as $\widehat{\alpha} \to \infty$.

For the discontinuous Galerkin formulation, we first consider the nonoverlapping method. We note that $\max_{\substack{K_{mk}\\ m>k}} \max_{e\subset\partial K_{mk}} W_e \lesssim 1$, and that the DG indicator $\beta(\alpha) = 0$ because the coefficient is continuous across the coarse grid boundaries as well as the zero Dirichlet boundary condition. Taking $\rho = 1$ in Theorem 3.3 implies that $\gamma_{DG}^{MS,L}(\alpha) \lesssim \frac{H}{h}$. It then follows from Theorem 3.1 that the nonoverlapping method has a bound which is independent of the jumps. For the overlapping method, we have $\pi(\alpha) = \delta_i^2 \|\alpha|\nabla\chi_i|^2\|_{L^\infty(\Omega)} \lesssim 1$, thus in this case the multiscale basis function with linear boundary condition will yield a robust bound. We note that, in this example, the multiscale basis function with oscillatory boundary condition is the same as the one with linear boundary condition.

The numerical results in Table 1 show that, both the nonoverlapping and overlapping method with multiscale coarse basis functions with linear boundary conditions are robust as predicted by the theory. The overlapping method [5] with the same multiscale coarse basis functions produces almost the same condition number estimates, however, for the linear coarsening, the results in Table 1 show a loss of robustness of the overlapping Schwarz method as $\widehat{\alpha}$ goes from 10^0 to 10^6.

Table 1: Condition number estimates of the Schwarz methods on Example 4.1 with $h = 1/128$, $H = 8h$, $\delta = 2h$, and $\eta = 4$.

	Discontinuous Galerkin			Continuous Galerkin	
	Nonoverlapping	Overlapping		Overlapping	
$\widehat{\alpha}$	MS, L	MS, L	$\gamma_{DG}^{MS,L}(\alpha)$	MS, L	L
10^0	26.79	6.43	1.00	5.64	5.6
10^2	21.61	6.44	1.42	5.79	58.6
10^4	21.49	6.81	1.44	5.80	358.3
10^6	21.49	6.81	1.44	5.80	378.7

In our next experiments, we study the behavior with different penalty terms. As we can see from Table 2, the condition number estimate for the nonoverlapping method grows linearly with the penalty parameter η. However, it is almost constant for the overlapping method, which suggests that the condition number bound do not depend on the penalty parameter. The results in Table 2 is in agreement with Theorem 3.1 and Theorem 3.2.

Table 2: Discontinuous Galerkin formulation on Example 4.1. Condition number estimates of the Schwarz method with $h = 1/128$, $H = 8h$ and $\delta = 2h$(only for overlapping).

	Nonoverlapping method			Overlapping method		
$\widehat{\alpha}$	$\eta = 5$	$\eta = 10$	$\eta = 100$	$\eta = 5$	$\eta = 10$	$\eta = 100$
10^0	33.14	64.88	635.2	6.47	6.56	6.88
10^2	26.55	51.09	487.3	6.73	6.87	6.96
10^4	26.39	50.74	483.4	6.83	6.89	6.99
10^6	26.40	50.73	483.4	6.83	6.89	6.99

Remark 4.1. Note that, in our numerical experiments, we test the model problem with zero Dirichlet boundary condition, thus all the degrees of freedom are inside domain Ω, which means that our DG indicator $\beta(\alpha)$ defined in (3.11) is only for $\partial K_{mk} \subset \Omega$ but not for the coarse grid boundaries on $\partial\Omega$. Moreover, in Example 4.1, since the coefficient of the conductivity field is continuous across coarse grid boundaries, we have $\beta(\alpha) = 0$ due to the fact that the jump of the coarse basis functions corresponding to the same coarse node is equal to 0. From Theorem 3.1, we know that the condition number bound for the nonoverlapping case will be

$$\eta \max_{\substack{\partial K_{mk} \\ m>k}} \max_{\substack{e_{jl} \subset \partial K_{mk} \\ j>l}} W_e \gamma(1) \frac{H}{h} + \gamma(\alpha),$$

taking $\rho = 1$ in Theorem 3.3 we have $\gamma(\alpha) \lesssim \frac{H}{h}$, thus theoretically speaking, the condition number bound will grow linearly with the penalty parameter η. While for the overlapping case, From Theorem 3.2, we know that the condition number bound for the overlapping case will be

$$\pi(\alpha) \max(\gamma(1), \beta(1)) \max_i \frac{H_i}{\delta_i} + \gamma(\alpha),$$

taking $\rho = 1$ in Theorem 3.3 implies $\gamma(\alpha) \lesssim \frac{H}{h}$, thus in this case, our condition number bound will keeps unchanged independent of the penalty parameter η. Both of the two cases are matched exactly by our numerical experiments in Table 2.

Example 4.2. In this example, the high conductivity field is no longer contained inside, it touches the coarse grid boundaries, see Figure 3 and Figure 4. In Figure 3, The conductivity field $\alpha(x)$ corresponds to a binary medium with background $\alpha(x)$ being equal to one, and $\alpha = \widehat{\alpha}$ on the channels with an area equal to $2h \times 4h$ each. In Figure 4, the high conductivity channels with diameter $2h \times 2h$ are located only on one side of the coarse grid boundaries.

We first compare the behavior of our nonoverlapping method on the two cases shown in Figure 3 and Figure 4. For the the conductivity field given in Figure 3, $\gamma(\alpha) \lesssim \frac{H}{h}$ since $\max_K \max_{e \subset \partial K} W_e = \widehat{\alpha}$, $\gamma(\alpha) \lesssim \frac{H}{h}$ (taking $\rho = 1$ in Theorem 3.3), and $\beta(\alpha) = 0$. Thus Theorem 3.1 predicts that the condition number bound will grow as $\widehat{\alpha} \to \infty$. However, for the conductivity field in Figure 4, we



Figure 3: Example 4.2 with $\alpha(x)$ crossing the coarse grid boundaries, $\alpha(x) = \widehat{\alpha}$ on the channels and $\alpha(x) = 1$ otherwise.



Figure 4: Example 4.2 with $\alpha(x)$ touching the coarse grid boundaries, $\alpha(x) = \widehat{\alpha}$ on the channels and $\alpha(x) = 1$ otherwise.

have $\max_K \max_{e \subset \partial K} W_e \lesssim 1$, $\gamma(\alpha) \lesssim \frac{H}{h}$ (taking $\rho = 1$ in Theorem 3.3), and $\beta(\alpha) \lesssim \frac{H}{h}$ (taking $\rho = 1$ in Theorem 3.4). Theorem 3.1 predicts that the bound is robust in this case. For the overlapping method, it is easy to see that $\pi(\alpha) \lesssim \max_i \delta_i^2 \|\alpha \nabla |\chi_i|^2\|_{L_\infty(\Omega)} \lesssim \delta_i^2/h^2 \approx 1$. It follows from Theorem 3.2 that the condition number bound will be independent of the jumps for both the conductivity field in Figure 3 and in Figure 4. The numerical results in Table 3 confirm these results.

Table 3: Discontinuous Galerkin formulation on Example 4.2. Condition number estimates for the Schwarz method with $h = 1/128$, $H = 8h$, $\delta = 4h$, and the penalty parameter $\eta = 4$.

	Nonoverlapping		Overlapping	
$\widehat{\alpha}$	Fig 3	Fig 4	Fig 3	Fig 4
10^0	2.68e+1	26.79	6.23	6.24
10^2	5.00e+2	28.91	7.17	7.15
10^4	4.76e+4	28.95	7.23	7.17
10^6	4.76e+6	28.96	7.23	7.17

Example 4.3. [Gaussian random field] In this example, we test our method on a more realistic model. The coefficient α is a realisation of a log-normal random field (see Figure 5), i.e., $\log \alpha(x)$ is a realisation of a homogeneous isotropic Gaussian random field with spherical covariance function, mean 0. This is a commonly studied model in the multiscale area in many literatures [5, 6]. There are some evidences from field data that this gives a reasonable presentation of reality in certain cases [15, 16]. There are many good ways to generate such random fields, we simply follow the way in [19] which used FFT (Fast Fourier Transformation) method [17, 18]. The spherical covariance function has a parameter θ, a bigger θ increases the correlation of the random field.



Figure 5: 256 × 256 Gaussian random field with covariance parameter $\theta = 50$.

Table 4: Condition numbers (iteration numbers) of Schwarz methods on Example 4.3 with $h = 1/128$, $H = 8h$, $\delta = 2h$, and $\eta = 4$.

	Discontinuous Galerkin		Continuous Galerkin
	Nonoverlapping	Overlapping	Overlapping
High Contrast	MS, OSC	MS, OSC	MS, OSC
8.55e+3	30.72 (52)	7.20 (16)	6.65 (15)
1.75e+5	32.68 (57)	7.85 (18)	7.12 (16)
7.32e+7	36.40 (67)	9.86 (21)	8.45 (19)
1.49e+9	37.90 (73)	11.27 (22)	9.38 (20)
6.02e+11	45.94 (86)	14.77 (25)	11.73 (22)
1.28e+13	51.61 (96)	16.80 (26)	13.28 (25)

In the numerical experiments, we compared the condition number estimates (iteration numbers) of both the nonoverlapping and overlapping domain decomposition method with the method [5].

5 Conclusions

In this paper, we present two two level additive Schwarz domain decomposition methods for the multiscale second order elliptic problem. The work here is an extension of related works, c.f., [4, 5], to a discontinuous Galerkin formulation, c.f., [13]. For the nonoverlapping case, we show that if the conductivity field do not cross the subdomain boundaries, our nonoverlapping method is robust. However, in some cases, when the conductivity field cross the subdomain boundaries, we show in Theorem 3.1 that our condition number estimate will be dependent on W_e, i.e., the weighted average of the coefficient over the edge e. It is now the topic of further investigation to see if we can get rid of this dependence on W_e. For the overlapping method, as seen in Theorem 3.2, we show that our method is robust under Assumption 3.1. We allow the discontinuity of the coefficients across the coarse grid boundaries.

Acknowledegments The authors thank Professor Maksymilian Dryja for a fruitful discussion on the paper and, in particular, for his valuable comments on the discontinnuous Galerkin method.

REFERENCES

[1] D. A. Adams, Sobolev Spaces, Academic Press, New York(1975).

[2] Barry F. Smith, Petter Bjørstad, William Gropp, Domain Decomposition: Parallel Multilevel Methods for Elliptic Partial Differential Equations, Cambridge University Press(1996).

[3] Petter Bjørstad, Maksymilan Dryja, Eero Vainikko, Additive Schwarz Methods without Subdomain Overlap and New Coarse Spaces, Proceedings from the 8th. International conference on domain decomposition methods(1996), John Wiley & Sons(1997).

[4] M. Dryja, M. Sarkis, Additive average Schwarz methods for discretization of elliptic problems with highly discontinuous coefficients, Computational Methods in Applied Mathematics, **10**, 1-13(2010).

[5] I. G. Graham, P. O. Lechner, R. Scheichl, Domain Decomposition for multiscale PDEs, Numer. Math., 589-626(2007).

[6] Cliffe, K. A., Graham, I. G., Scheichl, R., Stals, L., Parallel computation of flow in heterogeneous media modelled by mixed finite elements. J. Comp. Phys., **164**, 258-282(2000).

[7] Susanne C. Brenner, L. Ridgway Scott, The mathematical theory of finite element methods, Springer(2002).

[8] Thomas Y. Hou, Xiaohui Wu, Zhiqiang Cai, Convergence of a multiscale finite element method for elliptic problems with rapidly oscillating coefficients, 913-943(1999).

[9] Ivan Lunati, Patrick Jenny, Multiscale finite-volulme method for density-driven flow in porous media, Comput. Geosci., 337-350(2008).

[10] Ivan Lunati, Patrick Jenny, Multiscale finite-volume method for compressible multiphase flow in porous media, Journal of Computational Physics, 616-636(2006).

[11] J. Galvis, Y. Efendiev, Domain decomposition preconditioners for multiscale flows in high-contrast media, Multiscale Model Simul., **8**, 1461-1483(2010).

[12] A. Toselli, O. Widlund, Domain Decomopsition Methods-Algorithm and Theory, Springer-Verlag Berlin Heidelberg(2005).

[13] Zhiqiang Cai, Xiu Ye, Shun Zhang, Discontinuous Galerkin finite element methods for interface problems: a priori and a posteriori error estimations, SIAM J. Numer. Anal., **49**(2011).

[14] Xiaobing Feng, Ohannes A. Karakasshian, Two-level additive Schwarz methods for a discontinous Galerkin approximation of second order elliptic problems, SIAM J. Numer. Anal., **39**, 1343-1365(2001).

[15] L. W. Gelhar, A Stochastic Conceptual Analysis of One-Dimensional Groundwater Flow in Nonuniform Homogeneous Media, Water Resour. Res., **11**, 725-741(1975).

[16] R. J. Hoeksema and P. K. Kitanidis, Analysis of the Spatial Structure of Properties of Selected Aquifers, Water Resour. Res., **21**, 563-572 (1985).

[17] Feng Ruan, and Dennis Maclaughlin, An efficient multivariate random field generator using the fast Fourier transform, Advances in Water Resources, **21**, 385-399(1998).

[18] M. L. Robin, A. L. Gutjahr, E. A. Sudicky, and J. L. Wilson, Cross-correlated Random Field Generation with the Direct Fourier Transform Method, Water Resour. Res., **29** , 2385-2398(1993).

[19] Kozintsev, B., Kedem, B.: Gaussian package, University of Maryland. Available at http://www.math.umd.edu/ bnk/bak/generate.cgi (1999)

Authors address:
Yunfei Ma and Xuejun Xu, Institute of Computational Mathematics and Scientific/Engineering Computing, Academy of Mathematics and Systems Science, Chinese Academy of Sciences, Beijing 100190, China. mayf@lsec.cc.ac.cn, xxj@lsec.cc.ac.cn.

Petter Bjørstad, Department of Informatics, University of Bergen, Thormøhlensgate 55, 5008 Bergen, Norway. Petter.Bjorstad@ii.uib.no.

Talal Rahman, Faculty of Engineering, Bergen University College, Nygårdsgaten 112, 5020 Bergen, Norway. Talal.Rahman@hib.no.